

# Test Equipment Solutions Datasheet

Test Equipment Solutions Ltd specialise in the second user sale, rental and distribution of quality test & measurement (T&M) equipment. We stock all major equipment types such as spectrum analyzers, signal generators, oscilloscopes, power meters, logic analysers etc from all the major suppliers such as Agilent, Tektronix, Anritsu and Rohde & Schwarz.

We are focused at the professional end of the marketplace, primarily working with customers for whom high performance, quality and service are key, whilst realising the cost savings that second user equipment offers. As such, we fully test & refurbish equipment in our in-house, traceable Lab. Items are supplied with manuals, accessories and typically a full no-quibble 2 year warranty. Our staff have extensive backgrounds in T&M, totalling over 150 years of combined experience, which enables us to deliver industry-leading service and support. We endeavour to be customer focused in every way right down to the detail, such as offering free delivery on sales, covering the cost of warranty returns BOTH ways (plus supplying a loan unit, if available) and supplying a free business tool with every order.

As well as the headline benefit of cost saving, second user offers shorter lead times, higher reliability and multivendor solutions. Rental, of course, is ideal for shorter term needs and offers fast delivery, flexibility, try-before-you-buy, zero capital expenditure, lower risk and off balance sheet accounting. Both second user and rental improve the key business measure of Return On Capital Employed.

We are based near Heathrow Airport in the UK from where we supply test equipment worldwide. Our facility incorporates Sales, Support, Admin, Logistics and our own in-house Lab.

All products supplied by Test Equipment Solutions include:

- No-quibble parts & labour warranty (we provide transport for UK mainland addresses).
- Free loan equipment during warranty repair, if available.
- Full electrical, mechanical and safety refurbishment in our in-house Lab.
- Certificate of Conformance (calibration available on request).
- Manuals and accessories required for normal operation.
- Free insured delivery to your UK mainland address (sales).
- Support from our team of seasoned Test & Measurement engineers.
- ISO9001 quality assurance.

Test equipment Solutions Ltd  
Unit 8 Elder Way  
Waterside Drive  
Langley  
Berkshire  
SL3 6EP

T: +44 (0)1753 596000

F: +44 (0)1753 596001

Email: [info@TestEquipmentHQ.com](mailto:info@TestEquipmentHQ.com)

Web: [www.TestEquipmentHQ.com](http://www.TestEquipmentHQ.com)



# Electrometers

High-Speed and High-Accuracy Measurement of  $10^{-14}$  A and  $3 \times 10^{16} \Omega$

## R8340/8340A

- Measurement of Micro Current from 10 fA to 19.999 mA
- Measurement of High Resistance from 10  $\Omega$  to  $3 \times 10^{16} \Omega$
- High-Speed Charge/Discharge
- High-Speed Measurement with 100 Samples/Second
- Floating Measurement of 550 VDC (R8340) and 1100 VDC (R8340A)
- Standard GPIB Interface



(Photo is R8340)

## R8340/8340A

### Digital Ultra-High Resistance/Micro Current Meters

The R8340/8340A digital ultra-high resistance/micro current meters use an input amplifier gain switching type I-V converter, high-speed sampling A/D converter and low-noise high-response voltage generator. They are fast and precise, with a range from 10 fA to 19.999 mA for current measurement and 10  $\Omega$  to  $3 \times 10^{16} \Omega$  for resistance measurement.

The R8340/8340A have a continuously variable DC power supply with a voltage from 0.000 V to 1000.0 V as a voltage source for measuring high resistance. They can be used to test and inspect electric insulation materials such as synthetic resin and rubber, switches, connector and capacitors. With the use of accessories R12704 and R172708, surface resistivity rate, volume resistivity rate and the effect of temperature on both rates can be measured.

For micro current measurement, ion current and leak current can be measured with high sensitivity and precision.

The meters have a handler interface to be connected with external devices such as automatic handlers and fixtures. Packed format output is used for higher efficiency in GPIB data transfer, so improved throughput is guaranteed in production lines and incoming inspections.

The meter is provided with the sequence program function to store measurement conditions and procedures, allowing measurements under the same measurement conditions at the touch of a button. The contact check function makes it possible even for beginners to perform simple, stable and highly precise measurement.

### ■ Measurement Speed Selectable Depending on the Required Measurement Accuracy

The R8340/8340A are provided with the function to select the input resistance and integrating time by input amplifier gain switching. The measurement speed can be selected according to the measurement accuracy required, thus ensuring highly reliable measurement.

### ■ High-Speed Charging/Discharging of Samples

The built-in voltage generator has a low-noise (5 mVp-p/1,000 V) high-response (3 ms from 0 to 1,000 V) 10W-class power supply that enables the use as source and sink, allowing samples to be charged and discharged very quickly. In addition, the current limit value can be selected both for source and sink.

### ■ Sequence Program Function Assures Consistent Measurement Results

The R8340/8340A's sequence program function has several measurement sequences in addition to JIS C5102 measurement procedures and conditions as standard. The function makes it possible to store the set measurement conditions, allowing the same results to be obtained even if the measurement is performed by different engineers.

### ■ Stable Measurement of Grounded Samples

The R8340 is provided with the floating measurement capability for 550 Vpeak and the R8340A the floating measurement capability for 1100 Vpeak, allowing samples to be measured even with one end of a coaxial cable grounded.

Model	Max. Voltage Generation	Voltage Between Grounding	BCD, Analog Output
R8340	1000V	DC550V	None
R8340A	1000V	DC1100V	Possible

### Specifications

#### DC Current Measurement

Measuring range	Maximum display	Resolution	Measuring temperature $\pm$ (% of reading + digit)	Temperature coefficient $\pm$ (% of reading + digit)/°C	Settling time
200 pA	199.99 pA	10 fA	0.7+6	0.02+0.5	250 ms
2 nA	1999.9 pA	100 fA	0.7+3	0.02+0.2	25 ms
20 nA	19.999 nA	1 pA	0.3+3	0.01+0.2	5 ms
200 nA	199.99 nA	10 pA	0.3+3	0.01+0.2	
2 $\mu$ A	1999.9 nA	100 pA	0.15+3	0.005+0.2	2 ms
20 $\mu$ A	19.999 pA	1 nA	0.15+2	0.005+0.1	
200 $\mu$ A	199.99 $\mu$ A	10 nA	0.1+2	0.005+0.1	
2 mA	1999.9 $\mu$ A	100 nA	0.1+2	0.005+0.1	
20 mA	19.999 mA	1 $\mu$ A	0.1+2	0.005+0.1	

The measurement accuracy is the value under the following condition: the automatic calibration is on, temperature is  $+23^{\circ}\text{C} \pm 5^{\circ}\text{C}$ , relative humidity is 70% or less, for six months. It is indicated by  $\pm$  (% of reading + digit). The temperature coefficient is the value when the temperature is 0 to  $40^{\circ}\text{C}$  and the relative humidity is 70% or less, indicated by  $\pm$  (% of reading + digit)/°C.

The settling time indicates the time to reach  $\pm 1\%$  of the final value when the input amplifier gain is set to  $\times 10000$ , excluding range switching time.

#### Resistance Measurement

Current range	Measuring range ( $\Omega$ )	Measurement accuracy (VS 100 V, input amplifier gain is $\times 10$ or more)
200 pA	$1 \times 10^9$ to $3 \times 10^{16}$	0.8% + 14d
2 nA	$1 \times 10^8$ to $3 \times 10^{15}$	0.8% + 11d
20 nA	$1 \times 10^7$ to $3 \times 10^{14}$	0.4% + 11d
200 nA	$1 \times 10^6$ to $3 \times 10^{13}$	0.4% + 11d
2 $\mu$ A	$1 \times 10^5$ to $3 \times 10^{12}$	0.25% + 11d
20 $\mu$ A	$1 \times 10^4$ to $3 \times 10^{11}$	0.25% + 10d
200 $\mu$ A	$1 \times 10^3$ to $3 \times 10^{10}$	0.2% + 10d
2 mA	$1 \times 10^2$ to $3 \times 10^9$	0.2% + 10d
20 mA	$1 \times 10^1$ to $3 \times 10^8$	0.2% + 10d

Measurement accuracy:

$$\pm \{(\text{current range accuracy}) + (\text{voltage generation accuracy})\}$$

$$- \frac{\text{Input voltage drop}}{\text{generated voltage}}$$

Temperature coefficient:

$$\pm \{(\text{current measurement range temperature coefficient}) / ^{\circ}\text{C} + (\text{voltage measurement range temperature coefficient}) / ^{\circ}\text{C}\}$$

Maximum display: One to four digits (1 to 9.999)

Settling time: Varies with the current measuring range.

#### Input Resistance

Current range	Input amplifier gain switching			
	$\times 1$	$\times 10$	$\times 100$	$\times 10000$
200 pA	10 G $\Omega$	1 G $\Omega$	100 M $\Omega$	10 k $\Omega$ or less
2 nA	1 G $\Omega$	100 M $\Omega$	10 M $\Omega$	1 k $\Omega$ or less
20 nA	100 M $\Omega$	10 M $\Omega$	1 M $\Omega$	100 $\Omega$ or less
200 nA	10 M $\Omega$	1 M $\Omega$	100 k $\Omega$	11 $\Omega$ or less
2 $\mu$ A	1 M $\Omega$	100 k $\Omega$	10 k $\Omega$	2 $\Omega$ or less
20 $\mu$ A	100 k $\Omega$	10 k $\Omega$	1 k $\Omega$	1 $\Omega$ or less
200 $\mu$ A	10 k $\Omega$	1 k $\Omega$	100 $\Omega$	1 $\Omega$ or less
2 mA	1.1 k $\Omega$	110 $\Omega$	11 $\Omega$	1 $\Omega$ or less
20 mA	180 $\Omega$	18 $\Omega$	3 $\Omega$	1 $\Omega$ or less

Input voltage drop:  $\pm$  (measuring current  $\times$  input resistance + 500 $\mu$ V)

Input bias current: 30 fA or less (temperature  $+23^{\circ}\text{C} \pm 1^{\circ}\text{C}$ , relative humidity 50% or less)

Input capacitance: 30 pF or less (excluding the input cables)

Maximum voltage: 1.1 k Vpeak

#### DC Voltage Generation

Output voltage	Set resolution	Generation accuracy $\pm$ (% of setting + digit)	Temperature coefficient $\pm$ (% of setting + digit)/°C	Output noise (10-500 Hz)
0.000V to 10.000V	2.5 mV	0.1 + 10 d (10 mV)	0.008 + 0.5 d (500 $\mu$ V)	1 mVp-p
10.003V to 100.00V	25 mV	0.1 + 8 d (80 mV)	0.008 + 0.3 d (3 mV)	2 mVp-p
100.03V to 1000.0V	250 mV	0.1 + 8 d (800 mV)	0.008 + 0.3 d (30 mV)	5 mVp-p

The measurement accuracy is the value under the following condition:

Temperature is  $+23^{\circ}\text{C} \pm 5^{\circ}\text{C}$ , relative humidity is 70% or less, for six months. It is indicated by  $\pm$  (% of reading + digit).

The temperature coefficient is the value when the temperature is 0 to  $40^{\circ}\text{C}$  and the relative humidity is 70% or less, indicated by  $\pm$  (% of reading + digit)/°C.

Output voltage	Current compliance setting		
	300 mA	100 mA	10 mA
0.000 V to 30.00 V	$\pm 300$ mA	$\pm 100$ mA	$\pm 10$ mA
30.03 V to 100.00 V	$\pm 100$ mA	$\pm 100$ mA	$\pm 10$ mA
100.03 V to 1000.0 V	$\pm 10$ mA	$\pm 10$ mA	$\pm 10$ mA

Current compliance accuracy (source/sink):

When temperature is  $+23^{\circ}\text{C} \pm 5^{\circ}\text{C}$  and relative humidity is 70% or less

300 mA:  $\pm 300$  mA to  $\pm 500$  mA

100 mA:  $\pm 100$  mA to  $\pm 150$  mA

10 mA:  $\pm 10$  mA to  $\pm 20$  mA

Settling time: Pure resistive load  $t = 3$  ms (max.)

$$\text{Capacitive load } t = \frac{CV}{i} \text{ (charging time) } + t_0 \text{ (convergence time)}$$

t: Settling time (Time to reach  $\pm 1\%$  of the final value, excluding range switching time at forward resistance load)

C: Capacitive load

V: Output voltage

i: Charging current (The maximum value is the current compliance.)

t0: Convergence time (See the table below.)

Output voltage	Capacity	0.22 $\mu$ F	22 $\mu$ F	33 $\mu$ F
0.000 V to 100.00 V	0.1	0.1	3.0	7.0
100.3 V to 1000.0 V	4.2	15	150	

(msec)

Overshoot voltage:

Output voltage	Capacity	Pure resistance	0.22 $\mu$ F	22 $\mu$ F	33 $\mu$ F
0.000 V to 100.00 V	0.05	0.05	3.0	3.0	
100.3 V to 1000.0 V	0.05	36	24	10	

(V)

Measurement speed, maximum indication (in current measurement) :

Integration time	Number of samplings during free run	Maximum display
2 ms	100 times/s <sup>-1</sup>	3 1/2-digit 1999
1 PLC	50 Hz: 30 times/s	4 1/2-digit 19999
	60 Hz: 33 times/s	
5 PLC	8.5 times/s	
10 PLC	4.5 times/s	
4 $\times$ 10 PLC	1 times/s	
8 $\times$ 10 PLC	0.5 times/s	
16 $\times$ 10 PLC	0.3 times/s	

\*1: When display is OFF, automatic calibration is OFF and memory store is ON.

#### Other Functions

**NULL function:**  $R = X - X_{NULL}$

Subtracts the measurement data when NULL is set from the measurement data.

X: Measurement data

$X_{NULL}$ : Measurement data when NULL is set

**COMPARE Function:**

R(Hi):  $X > Y$ , R(Go):  $Y \beta X \beta Z$

R(Lo):  $X < Z$

# Electrometers

High-Speed and High-Accuracy Measurement of  $10^{-14}$  A and  $10^{16}$   $\Omega$

## R8340/8340A

Compares the measurement data with the set data.

X: Measurement value Y: High level set value  
Z: Low level set value

PRGM (sequence program) function: Major sequences such as capacitor leak measurement and JIS C5102 are built in.

CONTACT (contact check) function: Checks the contact of materials by C measurement. Checks capacitor with insufficient capacities by initializing standard sample.

Set item CONTACT LEVEL: Judgment at n times the standard sample

Automatic range level function: When the automatic current measurement range is set to UP, the level can be selected from 20000, 2000, or 200; when it is set to DOWN, the level can be selected from 1799, 179, or 17. This enables fast response measurement according to the number of required digits.

Data memory: 1000 data items can be stored.

Buzzer: The buzzer reports Hi/Lo of the COMPARE calculation results, program end and abnormality in two tones.

### I/O Functions

**GPIO interface:** Conforms to IEEE and 488-1978.

Outputs measurement data, generated voltage, status and error messages.

Binary packed format (IEEE 754 floating decimal point) is available.

**Handler interface:** I/O signal to time external devices such as automatic handler and fixture (24-pin Amphenol connector)

**Input:** \*TRIGGER, LID SIGNAL, STBY

**Output:** \*COMPLETE, \*EOM, \*INDEX, \*ALARM,  
\*LO, \*GO, \*HI, \*NO CONTACT

**Single wire signal (BNC connector):**

\*TRIGGER (input),  
LID SIGNAL (input),  
\*COMPLETE (output)

**BCD output (R8340A only):** The output format can be selected from OFF, BCD, or BINARY (50-pin Amphenol connector). TTL positive logic

**D/A output (R8340A only):** Converts any 2- or 3-digit display data to analog form and outputs them.

Output voltage:  $\pm 1$  V

Conversion output: Three-digit display 000 to  $\pm 999$  to  $\pm 0.999$  V  
+50% offset setting possible.

Output when offset: (-500 to 0 V, 000 to 0.5 V, +499 to 0.999 V)

Digit selection: 19999, 19999, 19999, 19999

Conversion accuracy:  $\pm 0.2\% \pm 2$  d (warranty for six months under  $23^\circ\text{C} \pm 5^\circ\text{C}$  and 70% RH)

Output resistance: 1  $\Omega$  or less

Maximum load current:  $\pm 0.5$  mA

Output connector: Binding post

### General Specifications

**Normal mode noise rejection rate:** (at 50/60 Hz  $\pm 0.09\%$ )

Integration time	NMRR	ECMRR
2 ms	0 dB	60 dB or more
1 PLC to 16 x 10 PLC	60 dB or more	120 dB or more

**Effective common mode noise rejection ratio:** ECMRR shown above  
(1 k $\Omega$  unbalanced impedance between LO and GND terminals, DC and 50/60 Hz  $\pm 0.09\%$ )

**Measurement method:** Integration method

**Input method:** Floating method

**Data display:** Seven-segment green LED

**Unit/indicator display:** 5 x 7 dot matrix green LED

**Input terminal:** Triaxial connector (INPUT)

Black binding post (LO, GND)

Blue binding post (GUARD)

**Voltage output terminal:** Red binding post (V SOURCE)

**Input protection fuse:** 1 A fuse

**Maximum voltage applied between terminals:**

Between INPUT and other terminals: 1100 Vpeak (1 minute)

Between LO and GUARD: 550 Vpeak (1100 Vpeak for R8340A)

Between LO and GND: 550 Vpeak (1100 Vpeak for R8340A)

Between GUARD and GND: 1100 Vpeak

Between V SOURCE and other terminals:

When 0 V to 100.00 V is set, +100 Vpeak

When 100.03 V to 1000.0 V is set, +1000 Vpeak

**Warm-up time:** Approx. 30 min

(Time to reach the specified accuracy)

**Operating environment:** Temperature  $0^\circ\text{C}$  to  $40^\circ\text{C}$ ,

Relative humidity 85% or less

**Storage temperature:**  $-25$  to  $70^\circ\text{C}$

**Power supply:** Specified at the time of ordering.

Option No.	Standard	31	32	42	43	44
Power supply voltage (V)	90 to 110	103 to 127	108 to 132	198 to 242	207 to 250	216 to 250
	48 to 66 Hz					

**Power consumption:** 90 VA or less

**Dimensions:** Approx. 424(W) x 88(H) x 350(D) mm

**Mass:** 8 kg max.

### Standard Accessories

Name	Model name	Product code	Remarks
Power cable	A01402		
Input cable (for R8340)	A01019 - 100		TRIAx - alligator clip Banana tip - alligator clip
Input cable (for R8340A)	A01018 - 100		TRIAx - alligator clip Banana tip - alligator clip

### Accessories (Optional)

**A02706 EIA** Rack mount set A (with front handles)

**A02707 JIS** Rack mount set A (with front handles)

**A02716 EIA** Rack mount set B (without front handles)

**A02717 JIS** Rack mount set B (without front handles)

**A02701** Front handle set

**A01009-50, 100, 150, 200** Input cable (TRIAx-TRIAx connector)

**MC-04S x 01, x 02** Input cable (for connecting TRIAX and TR44)

**A01239-50, 100, 150, 200**

(High withstand voltage TRIAX-TRIAx connector)

**A04201** TRIAXI-TRIAxJ Adaptor

**A04202** TRIAXI-BNC P Adaptor 1

**A04203** TRIAXI-BNC P Adaptor 2

**A04207** BNCJ-MP Adaptor

**A04208** TRIAXI Receptacle

**TR40 Series** Electrometer Accessories

**R12600 Series** Test Lead

**R12700 Series** Test Fixture