

## Saving and Recalling Panel Setups

### PANEL SETUPS



PANEL  
SETUPS

Press  to access the menus used for saving or recalling configurations — panel setups — to non-volatile memory or floppy disk, or to memory card or portable hard disk (HDD) depending on options installed.

#### Recall Save

To choose to save a panel setup or recall one already saved. When “**Save**” is selected, *as shown here*, the “TO SETUP” menus appear. While when “**Recall**” is chosen, the “FROM SETUP” menus, *shown overleaf*, appear

#### TO SETUP 1 ...2 ...3 or ...4

For saving any of four possible setups.

#### to Card, Flpy or HDD

For saving a setup to floppy, memory card, or hard disk, depending on options.

PANEL SETUPS

Recall  
Save

FROM SETUP1  
04-JUN-1996  
09:40:43

FROM SETUP2  
24-MAY-1996  
14:25:00

FROM SETUP3  
01-APR-1996  
16:00:11

FROM SETUP4  
24-MAY-1996  
14:38:12

FROM DEFAULT  
SETUP

From Card  
Flpy or HDD

**Recall or Save**

To select for saving or recalling a panel setup. When **“Save”** is selected, *as shown on the previous page*, the **“TO SETUP”** menus appear. While when **“Recall”** is chosen, *as shown here*, the **“FROM SETUP”** menus appear.

**FROM SETUP 1 ...2 ...3 or ...4**

For recalling any of four possible saved setups. In the example shown here, all four possible setups have been stored. When no setup has been stored, that menu will indicate **“Empty”**.

**FROM DEFAULT SETUP**

To choose a default setup, already stored in the scope.

**from Card, Flpy or HDD**

For accessing the secondary **“RECALL SETUPS”** menu to recall a setup stored on floppy, card or portable hard disk, depending on the options installed.

---

## RECALL SETUPS

```
RECALL SETUPS
  From
  Card  Flpy
  HDD
  Directory:
  LECROY-1.DIR
  10-OCT-96
  09:52:12
  Size 3403
  DO RECALL
  ONE.PNL
  File
  ONE   PNL
  ZERO  PNL
```

### from

For selecting to recall a setup from floppy, or card or portable hard disk, depending on the options installed and the medium on which the desired setup is stored.

### DO RECALL

To perform the recall of the setup selected in the "File" menu (*see below*).

### File

For selecting the stored setup, using the attributed menu knob.