

# TLK2711-SP Unpowered Receiver Stress Evaluation

---

In response to a customer inquiry Texas Instruments HiRel Products undertook an investigation of the TLK2711-SP space-rated 1.6-GBPS to 2.5-GBPS transceiver (DLA SMD 5962-0522101VXC) to evaluate the effects of additional stresses that are encountered due to signals driven on an unpowered receiver.

## Contents

1	Introduction .....	1
2	Methodology .....	2
3	Summary .....	2
4	References .....	2

## Trademarks

All trademarks are the property of their respective owners.

## 1 Introduction

Per the TLK2711-SP data sheet ([SGLS307](#)) and the DLA Standard Microcircuit drawing [5962-05221 SMD](#), the absolute-maximum specification for the DINRXP and DINRXN pins is  $-0.35\text{-V}$  minimum to  $V_{DDA} + 0.35\text{-V}$  maximum. In the case where the receiving TLK2711-SP is unpowered, this results in a  $V_{DDA}$  of  $0\text{ V}$ . The minimum and maximum voltage level that can be applied under this circumstance is therefore  $-0.35\text{ V}$  to  $+0.35\text{ V}$ . Exceeding this range will cause the electrostatic discharge (ESD) protection diodes within the device to begin conducting.

Due to the age of the wafer fabrication process and technology used to create this device, direct analysis of the reliability impact of exceeding the absolute-maximum range is not practical from a design perspective. Therefore a stress test was devised to evaluate possible changes in functionality, performance, and/or parametrics.

Previously a stress test was performed on multiple units to determine the maximum cumulative exposure of unpowered receiver to external inputs. Characterization was performed using maximum VOD, minimum frequency and typical VCM from recommended operating conditions for a twenty hour period. This characterization determined that the TLK2711-SP showed no performance degradation when an external powered transmitter (a transmitting DC coupled TLK2711-SP was used) sends a signal to an unpowered receiver for short periods of time. This is specified in the data sheet under *Absolute Maximum Ratings* as up to ten hours over the lifetime of the device. Some customers, however, were unable to meet this duration over the specified mission lifetime. Consequently an additional stress test was performed with extended durations.

## 2 Methodology

Worst case conditions were determined to be DC coupling with slowest data frequency. This would conduct the highest current for longest duration. With respect to the device reliability, worst-case electromigration occurs with DC currents at high temperatures. Accordingly the following worst-case conditions were applied to units 101 through 103:

- DC coupled maximum VOD from 50-Ω source.
- DINRXP and DINRXN driven differentially with 700 mV to 1.8 V with 800-MHz clock (1.6Gbps equivalent).
- This results in a 1.25-V common mode with worst case 1100-mV VOD at 125°C.
- 125°C (maximum specified operating case temperature).
- Two units exposed to 240 hours, and one unit to extended duration of 1463 hours.

Three TLK2711-SP devices, labeled Unit-101 through Unit-103, and one control unit, labeled Unit-104, were characterized before and after the above stress conditions. Delta measurements were evaluated to determine if a shift occurred with respect to the receiver inputs. Table 1 shows the results of the parametric tests. Values are pre-post delta readings with a negative value indicating a decrease.

**Table 1. Parametric Test Results<sup>(1)</sup>**

Pin	Test	Unit-101	Unit-102	Unit-103	Unit-104	Unit
		Stress Duration = 240 hrs	Stress Duration = 240 hrs	Stress Duration = 1463 hrs	Stress Duration = 0 hrs	
RXN	Opens check	-3.98E-01	-4.06E-01	-4.26E-01	-3.55E-01	V
RXP	Opens check	-3.97E-01	-4.06E-01	-4.25E-01	-3.54E-01	V
RXN	Shorts check	2.89E-01	2.91E-01	2.84E-01	2.84E-01	V
RXP	Shorts check	2.90E-01	2.93E-01	2.85E-01	2.85E-01	V
RXN	Pin-to-pin check	1.86E-02	2.11E-02	2.49E-02	2.36E-02	V
RXP	Pin-to-pin check	1.20E-03	1.20E-03	-1.36E-03	-1.35E-03	V
RXN	Pin-to-pin leakage	1.43E-05	6.27E-06	1.43E-05	1.42E-05	A
RXP	Pin-to-pin leakage	-2.64E-06	-8.56E-06	-2.64E-06	-4.60E-06	A
RXN	IIH_IIL	-6.96E-06	-6.96E-06	3.49E-04	-6.96E-06	A
RXP	IIH_IIL	5.22E-06	5.22E-06	3.61E-04	7.20E-06	A
RXN	IIH_IIL	1.63E-05	2.63E-05	2.83E-05	2.83E-05	A
RXP	IIH_IIL	6.09E-06	1.27E-07	6.09E-06	4.10E-06	A

<sup>(1)</sup> This data is provided "AS IS" for informational purposes only. No statement is made nor is any warranty implied as to reliability or operating lifetime. TI warrants its products in accordance with TI's Terms of Sale (available at [www.ti.com/termsofsale](http://www.ti.com/termsofsale)). Customers are solely responsible to conduct sufficient engineering and additional qualification testing to determine whether a TI device is suitable for use in the customer's applications.

The orange highlighted data points represent a slight increase of RXP and RXN leakage current in Unit-103. The post-stress leakages were still within device data sheet limits.

## 3 Summary

All units passed the full functional and parametric production test program post stress. Only Unit-103 that was exposed to 1463 hours of stress showed marginal increase in IIH/IIL pin leakage due to extended stress.

## 4 References

- [TLK2711-SP 1.6-Gbps to 2.5-Gbps Class V Transceiver](#) (SGLS307)
- [DLA Standard Microcircuit drawing 5962-05221](#)

## IMPORTANT NOTICE FOR TI DESIGN INFORMATION AND RESOURCES

Texas Instruments Incorporated ("TI") technical, application or other design advice, services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using any particular TI Resource in any way, you (individually or, if you are acting on behalf of a company, your company) agree to use it solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources.

You understand and agree that you remain responsible for using your independent analysis, evaluation and judgment in designing your applications and that you have full and exclusive responsibility to assure the safety of your applications and compliance of your applications (and of all TI products used in or for your applications) with all applicable regulations, laws and other applicable requirements. You represent that, with respect to your applications, you have all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. You agree that prior to using or distributing any applications that include TI products, you will thoroughly test such applications and the functionality of such TI products as used in such applications. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

You are authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING TI RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY YOU AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

You agree to fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of your non-compliance with the terms and provisions of this Notice.

This Notice applies to TI Resources. Additional terms apply to the use and purchase of certain types of materials, TI products and services. These include; without limitation, TI's standard terms for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>), [evaluation modules](#), and [samples](http://www.ti.com/sc/docs/sampterm.htm) (<http://www.ti.com/sc/docs/sampterm.htm>).

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2018, Texas Instruments Incorporated