

Addendum to **MC68HC908LD64** **Technical Data**

This addendum provides corrections to:

MC68HC908LD64 Technical Data
(Motorola document number MC68HC908LD64/D Rev. 2.0)

Page 278: Correct WRDY description under **18.7.2 OSD Status Register**.

From: WRDY — OSD Buffer Write Ready

This bit is set when the OSD data registers \$0062 and \$0063, are ready to be loaded with new data. The WRDY is cleared after the CPU writes to the high byte register, \$0063. It becomes set again when the OSD circuitry has transferred the content of data registers to the OSD RAM. Reset sets this bit.

- 1 = OSD data buffers ready for new data
- 0 = OSD data buffers busy

To: WRDY — OSD Buffer Write Ready

This bit is set when the OSD data registers \$0062 and \$0063, are ready to be loaded with new data. The WRDY is cleared after the CPU writes to the low byte register, \$0062. It becomes set again when the OSD circuitry has transferred the content of data registers to the display RAM. Reset sets this bit.

- 1 = OSD data buffers ready for new data
- 0 = OSD data buffers busy

Page 279: Correct OSDD[15:0] description under **18.7.3 OSD Data Registers.**

From: OSDD[15:0] — OSD RAM 16-Bit Data Buffer

These bits store the data which is going to be written into the OSD RAM when OSDMEN is set. While OSD circuitry is displaying data from the display RAM, updates to the display RAM is made by writing to the OSD row and column address registers and this 8-bit pair data registers. The OSD buffer write ready bit, WRDY, will be cleared after the write to the high byte register, \$0063.

To: OSDD[15:0] — OSD RAM 16-Bit Data Buffer

While OSD circuitry is displaying data from the display RAM, update the display RAM (location specified by the row and column address registers, OSDRAR and OSDCAR) by writing data to the high byte register (OSDDRH) followed by the low byte register (OSDDRL). After writing to the OSDDRL, the OSD buffer write ready bit (WRDY) will be cleared. WRDY becomes set again when the OSD circuitry has transferred the content of the OSD data registers to the display RAM.

Page 288: Correct OSD_EN bit location under **18.8.3.5 Frame Control Registers**

From: Row 15, Column 15:

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
OSD_EN														VPOL	HPOL

To: Row 15, Column 15:

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
								OSD_EN						VPOL	HPOL

RoHS-compliant and/or Pb- free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb- free counterparts. For further information, see <http://www.freescale.com> or contact your Freescale sales representative.

For information on Freescale's Environmental Products program, go to <http://www.freescale.com/epp>.



Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document. Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.