



Click [here](#) to ask an associate for production status of specific part numbers.

## MAX32570

# Low-Power Arm Cortex-M4 Microcontroller with Contactless Radio for Secure Applications

### General Description

The MAX32570 DeepCover<sup>®</sup> secure microcontroller provides an interoperable, secure, and cost-effective solution to build new generations of trusted devices. It can be used in single-chip applications such as PIN pads, mobile POS (MPOS), and secure card reader for PIN (SCRIP), but also in dual-chip applications such as countertop and tablet POS. It includes all the essential functions to address those applications including a multi-protocol RF contactless controller and radio front-end, a dual smart card controller, a parallel camera interface, a magnetic stripe reader (MSR), a TFT controller, and a secure keypad controller.

The MAX32570 operates at 150MHz and is based on an Arm<sup>®</sup> Cortex<sup>®</sup>-M4 with FPU processor with 1MB flash, 760KB SRAM, 8KB OTP, 1KB of battery-backed AES self-encrypted nonvolatile SRAM (NVSRAM) and a 256-bit flip-flop-based battery-backed key storage. The flash memory is split into two banks of 512KB to provide flexibility when programming over the air. Error correction coding (ECC) (single-error correction double-error detection, or SEC-DED) for flash and SRAM provides extremely reliable code execution. The device embeds both secure public and private key cryptographic algorithms and a true random number generator (TRNG) compliant with SP-800-90A and SP-800-90B standards. It also features a number of security protections and detectors to enforce system integrity including a dynamic sensor controller, environmental sensors, and fault detectors.

The device features five flexible power modes. Multiple SPI, UART, and I<sup>2</sup>C serial interfaces, as well as a QSPI, 1-Wire<sup>®</sup> master, a USB 2.0 High-Speed device, and an optional 10/100 Ethernet MAC, allow for greater connectivity. Some device package variants offer flexible off-chip memory expansion that supports SD/SDHC, SDIO/eMMC cards, QSPI flash, and SRAM memories with eXecute In Place (XIP), encryption, and authentication. The device is available in a number of package variants, ranging from 121-pin BGA to 169-pin BGA, 0.65mm pitch packages.

### Applications

- Secure Card Reader for PIN (SCRIP)
- PCI Mobile Payment Terminals (MPOS)
- Countertop and Tablet POS
- Contact/Contactless PIN Pads
- ATM Keyboards

### Benefits and Features

- High-Efficiency Microcontroller for Secure Battery-Powered Applications
  - Arm Cortex-M4 Processor with FPU up to 150MHz
  - 150MHz and 75MHz Internal Oscillators
  - Low-Power 7.37MHz System Clock Option
  - 1MB Flash, Organized into Dual Banks 2 x 512KB
  - 760KB (608KB ECC) SRAM
  - Optional Error Correction Code (ECC-SEC-DED) for Cache, SRAM, and Internal Flash
  - 1KB AES Encrypted NVSRAM, 8KB Internal OTP
- Scalable Cached External Memory Interfaces
  - QSPI Flash with AES-GCM and XiP
  - QSPI SRAM with AES-GCM and XiP
  - 150Mbps SDHC/eMMC/SDIO/microSD Interface
- Security Features Facilitates System-Level Protection
  - ISO 14443A/B, JIS X 6319-4, ISO 15693 Contactless Reader with Internal Transceiver
  - Secure Bootloader with Public Key Authentication
  - Hardware AES, DES, ECDSA and SHA-2 Engines
  - 10-Line Secure Keypad Controller
  - TRNG (SP-800-90A and SP-800-90B)
  - Six External Dynamic Tamper Sensors
  - Die Shield with Dynamic Random Signal
  - 1x 256-Bit and 2x 128-Bit Flip-Flop-Based AES Key Storage
  - Temperature and Voltage Tamper Monitor
  - Fault Detectors
- Optimal Peripheral Mix Provides Platform Scalability
  - 16-Channel DMA
  - One QSPI/SPI Master
  - Up to Three SPI Master (37.5MHz)/Slave (75MHz)
  - Up to Six UARTs with Flow Control
  - Up to Two ISO 7816 UART/Smart Card Controller
  - Up to Three 1MHz I<sup>2</sup>C Master/Slave
  - Up to Three Channels 7.8ksps 10-Bit Sigma-Delta ADC
  - USB 2.0 High-Speed Device Interface with PHY
  - 10/100 Ethernet MAC with RMII/MII Support
  - 24-Bit TFT LCD Controller
  - 12-Bit Parallel Camera Interface
  - Triple-Track Magnetic Stripe Head Interface
  - Eight Pulse Train Generators
  - Six 32-Bit Timers, Two HTimers
  - 1-Wire Master, Two Watchdog Timers
  - Real-Time Clock (RTC)

Arm and Cortex are registered trademarks of Arm Limited (or its subsidiaries) in the US and/or elsewhere.

DeepCover and 1-Wire are registered trademarks of Maxim Integrated Products, Inc.

19-100602; Rev 5; 7/22

[Ordering Information](#) appears at end of data sheet.

© 2022 Analog Devices, Inc. All rights reserved. Trademarks and registered trademarks are the property of their respective owners.

One Analog Way, Wilmington, MA 01887 U.S.A. | Tel: 781.329.4700 | © 2022 Analog Devices, Inc. All rights reserved.

# ABRIDGED DATA SHEET

MAX32570

Low-Power Arm Cortex-M4 Microcontroller  
with Contactless Radio for Secure Applications

## Ordering Information

PART	NFC	MSR	SPIXF/ SPIXR	EMAC	DEBUG PORT	ADC INPUTS	SDHC	TFT LCD	ISO- UART	PIN-PACKAGE
MAX32570-MBS+	No	No	Yes	Yes	No	1	Yes	No	2	121 BGA 8mm x 8mm x 1.11mm 0.65mm pitch
MAX32570-MBS+T	No	No	Yes	Yes	No	1	Yes	No	2	121 BGA 8mm x 8mm x 1.11mm 0.65mm pitch
MAX32570-MBJ+	No	No	Yes	Yes	Yes	1	Yes	No	2	121 BGA 8mm x 8mm x 1.11mm 0.65mm pitch
MAX32570-QBS+	Yes	Yes	Yes	Yes	No	3	Yes	Yes	2	169 BGA 9mm x 9mm x 1.2mm 0.65mm pitch
MAX32570-QBS+T	Yes	Yes	Yes	Yes	No	3	Yes	Yes	2	169 BGA 9mm x 9mm x 1.2mm 0.65mm pitch
MAX32570-QBJ+	Yes	Yes	Yes	Yes	Yes	3	Yes	Yes	2	169 BGA 9mm x 9mm x 1.2mm 0.65mm pitch
MAX32570-MNS+#	No	No	Yes	Yes	No	1	Yes	No	2	121 BGA 8mm x 8mm x 1.11mm 0.65mm pitch
MAX32570-MNS+T#	No	No	Yes	Yes	No	1	Yes	No	2	121 BGA 8mm x 8mm x 1.11mm 0.65mm pitch
MAX32570-MNJ+#	No	No	Yes	Yes	Yes	1	Yes	No	2	121 BGA 8mm x 8mm x 1.11mm 0.65mm pitch
MAX32570-QNS+#	Yes	Yes	Yes	Yes	No	3	Yes	Yes	2	169 BGA 9mm x 9mm x 1.2mm 0.65mm pitch
MAX32570-QNS+T#	Yes	Yes	Yes	Yes	No	3	Yes	Yes	2	169 BGA 9mm x 9mm x 1.2mm 0.65mm pitch
MAX32570-QNJ+#	Yes	Yes	Yes	Yes	Yes	3	Yes	Yes	2	169 BGA 9mm x 9mm x 1.2mm 0.65mm pitch

+Denotes a lead(Pb)-free/RoHS-compliant package.

T = Tape and reel. Full reel.

# Do not use for new designs. The pin configuration is different for these parts. Contact Analog Devices for further information.