

TUSB2077A Errata

1 Parts Affected

- TUSB2077A [SLLS414A](#), TUSB2046B [SLLS413B](#) and TUSB2036 [SLLS372B](#)

1.1 Symptoms

- TI has found that the TUSB2077A (also TUSB2046B and TUSB2036) has a slight violation in the manner that it determines the intended speed of an attached downstream device.

1.2 Description

By the intent of the USB specification (shown in Figure 7-19), the speed should be determined by sampling the DP or DM line following a 100ms debounce interval after either signal (DP or DM) first crosses the V_{IH} threshold. The TUSB2077A (TUSB2046B, TUSB2036) actually samples the speed at the first V_{IH} crossing and latches this value. This issue has only been observed recently with newer devices that either drive DM high or show excessive ringing during the initial connection, hence causing the speed detection to be seen as low speed by the TUSB2077A (TUSB2046B, TUSB2036). Note that this device is used extensively in the USB1.1 Goldtree suite, and this issue was never revealed, further pointing to the fact that some newer devices have less control on DM than previous devices, although this is allowed by the USB specification. TI has no planned fix in the pipeline, but wants users to be aware of this issue, which can easily be avoided by guaranteeing that DP be asserted high before DM. In the event that a false low speed detection is observed, the situation can be resolved by performing a `CLEAR_PORT_FEATURE(PORT_ENABLE)` followed by a `RESET_PORT` in the software driver, assuming both DP and DM are now stable.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
Low Power Wireless	www.ti.com/lpw	Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments
Post Office Box 655303 Dallas, Texas 75265