

Qty	Description	Reference Designator	Manufacturer	Part Number
1	74LVC14A SOIC14	U59	TI (R)	74LVC14AD
1	IDT74FCT3244APY SSOP20	U8	IDT (R)	IDT74FCT3244APYG
1	SN74LVC1G125 SOT23-5	U52	TI (R)	74LVC1G125DBVRE4
3	SN74LVC1G08 SOT23-5	U53-U55	TI (R)	SN74LVC1G08DBVR
1	SN65LVDS2D SOIC8	U50	NATIONAL S (R)	DS90LV018ATM
1	MIC2025-1 SOIC8	U69	DIGI-KEY (R)	576-1057-ND
4	74CBTLV3244 TSSOP20	U2,U5-U7	IDT (R)	IDT74CBTLV3244PGG
2	25MHZ OSC013	Y1,Y2	ABRACON (R)	ABM8-25.000MHZ-B2-T
1	24MHZ SMD	Y3	ABRACON (R)	ABM8-24.000MHZ-B2-T
17	74CBTLV1G125 SC70_5	U11,U12,U15-U19,U21-U24,U44,U45,U60-U62,U64	TI (R)	SN74CBTLV1G125DCKR
2	MCP23017 QFN28	U47,U48	MICROCHIP (R)	MCP23017T-E/ML
2	PI3C3125 TSSOP14	U27,U28	PERICOM (R)	PI3C3125LE
2	25MHZ OSCCC200X250	U31,U68	DIGI-KEY (R)	478-4780-1-ND
2	BSS308PE SOT23	Q1,Q2	INFINEON (R)	BSS308PE H6327
1	FT232R QFN32	U26	DIGI-KEY (R)	768-1008-1-ND
1	INA3221 QFN16	U57	TI (R)	INA3221AIRGVT
1	24MHZ OSCCC200X250	U30	AVX CORPOR (R)	KC2520B24.0000C10E00
1	25LC010AT SOT23-6	U4	DIGI-KEY	25LC010AT-I/OTTR-ND
1	ADM8828ARTZ SOT23-6	U72	ADI (R)	ADM8828ARTZ-REEL7
1	FZT953 SOT-223	VR2	DIGI-KEY (R)	FZT953CT-ND
1	MT41K128M16JT FBGA96	U9	DIGI-KEY (R)	MT41K128M16JT-125:K-ND
1	TJA1145T SOIC14	U58	DIGI-KEY	TJA1145T,118-ND

Qty	Description	Reference Designator	Manufacturer	Part Number
1	TJA1055/3 SOIC14	U39	NXP (PHILI (R)	TJA1055/3
1	SI4204 SOIC8	U56	VISHAY (R)	SI4204DY-T1-GE3
1	ADP5054 LFCSP48	VR3	ADI (R)	ADP5054ACPZ-R7
1	CS2100-CP MSOP10	U51	CIRRUS LOG (R)	CS2100CP-CZZ
1	SI5356A QFN24	U25	SILICON LA (R)	Si5356A-B03215-GM
2	25MHZ SMT	Y4,Y6	DIGI-KEY (R)	XC1781TR-ND
1	BCM89810 MLP48	U67	BROADCOM	BCM89810A2AMLG
1	TPS54340 HSOIC8	VR6	TI (R)	TPS54340DDAR
1	NCP4687DSN25 SOT23-5	VR1	ON SEMI	NCP4687DSN25T1G
1	DP83867IRRGZ QFN48	U49	TI	DP83867IRRGZT
1	ADP3338AKCZ-1.8 SOT-223	VR5	ADI (R)	ADP3338AKCZ-1.8-RL
1	AD8532ARZ SOIC8	U33	ADI (R)	AD8532ARZ-REEL7
4	AD8606ARZ SOIC8	U34-U37	ADI (R)	AD8606ARZ
1	ADG774ABRQZ QSOP16	U40	ADI (R)	ADG774ABRQZ-REEL
1	AD8022 MSOP8	U66	ADI (R)	AD8022ARMZ
1	ADP170AUJZ-1.2 TSOT5	VR4	ADI (R)	ADP170AUJZ-1.2-R7
1	ADAU1977 LFCSP40	U42	ADI (R)	ADAU1977WXCPCZ
1	ADAU1962AWBSTZ LQFP80	U38	ADI (R)	ADAU1962AWBSTZ
1	ADM6315 SOT143	U46	ADI (R)	ADM6315-29D2ARTZR7
1	ADAU1979WBCPZ LFCSP40	U41	ADI (R)	ADAU1979WBCPZ
1	ADP7104ACPZ LFCSP8	U71	ADI (R)	ADP7104ACPZ-R7
1	ADP1752-1.0 LFCSP16	U13	ADI	ADP1752ACPZ-1.0-R7
1	ADSP-SC573 LFBGA400	U1	ADI	ADSP-SC573CBCZ-4
1	RCA 4X2 CON011	J11	DIGI-KEY (R)	SC1537-ND
1	RCA 2X2 CON013	J3	DIGI-KEY (R)	PJRS2X2S01X-ND

Qty	Description	Reference Designator	Manufacturer	Part Number
1	MICTOR 38PIN CON015	P5	DIGI-KEY (R)	A32308-ND
2	DIP6 SWT017	SW6,SW7	DIGI-KEY (R)	CT2186LPST-ND
1	RCA 1X2 CON031	J12	SWITCHCRAF (R)	PJRS1X2S02X
1	IDC 4X2 IDC4X2_M_SMT	P25	SAMTEC (R)	TSM-104-01-T-DV
2	RJ11 4PIN CON039	J5,J6	TYCO ELECT (R)	5558872-1
1	DIP2 SWT020	SW8	C&K COMPON (R)	TDA02H0SB1
10	IDC 2X1 IDC2X1	P12-P18,P20,P21,P24	SAMTEC (R)	HTSW-102-07-T-S
1	3A RESETABLE SMD	F1	TYCO ELECT (R)	SMD300F-2
1	IDC 2PIN_JUMPER_SHORT	SJ?	SULLINS CO (R)	SPC02SYAN
1	3.5MM STEREO_JACK CON_CUI_SJ1-3525NG	J14	CUI INC (R)	SJ1-3525NG
1	IDC 2X1 IDC2X1_SMT	JP2	SAMTEC (R)	TSM-102-01-T-SV
2	IDC 3X1 IDC3X1_SMT	JP3,JP4	SAMTEC (R)	TSM-103-01-T-SV
1	ROTARY SWT027	SW1	DIGI-KEY (R)	563-1053-ND
1	SD_CONN 8-BIT CON067	J18	MORETHANAL (R)	MHC-W21-601-LF
3	0.6MM 120PIN HIROSE_FX8-120P-SV1(91)	P1A,P1B,P1C	HIROSE (R)	FX8-120P-SV1(91)
1	TEST LOOP LOOP_2838	GP1	DIGI-KEY (R)	5016KTR-ND
2	IDC 5X2 IDC5X2_SMT	P2,P3	SAMTEC (R)	TSM-105-01-T-DV
2	USB-MICRO 5PIN HIROSE_ZX62D-AB-5P8	P7,P23	Hirose Electric	ZX62D-AB-5P8(30)
1	PWR 2.1MM_JACK CUI-INC_PJ-102AH	P27	DIGIKEY	CP-102AH-ND
1	FIBER-OPTIC SPDIF EVERLIGHT_PLT133/T10	J1	DIGI-KEY (R)	1080-1430-ND
1	FIBER-OPTIC SPDIF EVERLIGHT_PLR135/T10	J10	EVERLIGHT (R)	PLR135/T10

Qty	Description	Reference Designator	Manufacturer	Part Number
1	5.08MM 2POS TH	P22	WEIDMULLER (R)	1760510000
1	0.05 10PIN SAMTEC_SHF-105-01-L-D-TH	P1	SAMTEC (R)	SHF-105-01-L-D-TH-TR
5	SMB 1PIN SMT	J2,J15-J17,J19	EMERSON	131-3711-201
1	QSH 40PIN SMT	J13	SAMTEC (R)	QSH-020-01-L-D-DP-A
1	RJ45 8PIN TH	J7	DIGI-KEY (R)	AE10387-ND
2	ERF8 10X2 SMT	J8,J9	SAMTEC (R)	ERF8-010-05.0-S-DV-L-TR
4	MOMENTARY SMT	SW2-SW4,SW9	APEM INC	ADTSMW64NVTR
1	ROTARY_ENCODER CUI_ACZ11BR4E-15FD1-20C	SW5	CUI	ACZ11BR4E-15FD1-20C
1	RJ45 With Magnetics	J4	DIGI-KEY	732-4970-ND
3	0.22UF 25V 10% 0805 X7R	C205,C206,C389	AVX CORPOR (R)	08053C224KAT2A
4	600 200MA 0603	FER20-FER23	DIGI-KEY (R)	490-1014-2-ND
8	600 500MA 1206	FER3,FER4,FER13,FER24,FER25,FER32,FER34,FER35	LAIRD	HZ1206E601R-10
4	1UF 16V 10% 0805 X7R	C395,C396,C415,C416	DIGI-KEY (R)	399-1284-2-ND
1	680PF 50V 1% 0805 NPO	C391	KEMET	C0805C681F5GACTU
12	10UF 16V 20% CAP002 ELEC	CT2-CT12,CT15	PANASONIC (R)	EEE1CA100SR
2	68UF 25V 20% CAP003	CT13,CT14	PANASONIC (R)	EEE-FC1E680P
1	0 1/8W 5% 0805	R386	DIGI-KEY (R)	P0.0ACT-ND
1	190 5A 2020	FER29	MURATA	DLW5BSM191SQ2L
13	10UF 6.3V 10% 0805 X5R	C15,C198,C212,C219,C226,C233,C309,C323,C339,C355,C380-C382	AVX CORPOR (R)	08056D106KAT2A
2	4.7UF 6.3V 10% 0805 X5R	C159,C283	AVX CORPOR (R)	08056D475KAT2A

Qty	Description	Reference Designator	Manufacturer	Part Number
87	0.1UF 10V 10% 0402 X5R	C1,C2,C12,C13,C18,C27,C68,C69,C86,C87,C89,C91-C94,C103,C105,C113,C115,C117,C122-C127,C129,C131,C132,C137-C140,C142,C152,C153,C157,C207,C239-C242,C257,C265,C277,C279,C280,C286-C289,C294,C295,C297,C301,C303-C305,C316,C318,C324-C328,C333,C337,C340-C344,C349,	KOA (R)	X7R0402CTTD104J
95	0.01UF 16V 10% 0402 X7R	C3-C11,C14,C16,C17,C20,C23,C24,C31-C34,C41-C45,C83,C84,C97,C110,C118-C121,C141,C199-C204,C210,C243-C250,C253-C255,C278,C281,C282,C319-C322,C329-C332,C334-C336,C338,C345-C348,C350-C352,C354,C361-C364,C366-C369,C372-C375,C377-C379,C385-C387,C393,C401,C423	AVX CORPOR (R)	0402YC103KAT2A
109	10K 1/16W 5% 0402	R6,R7,R19,R22,R33-R35,R37,R39,R41,R51-R57,R59,R66,R67,R69-R71,R73,R78-R84,R113,R123-R127,R140,R141,R143-R146,R191-R193,R195-R197,R243-R247,R249,R256,R259-R263,R266-R269,R273-R278,R294-R296,R298,R302,R305,R306,R309,R311,R314,R316,R350-R355,R360,R361,R370,R	YAGEO (R)	RC0402JR-0710KL
4	4.7K 1/16W 5% 0402	R102-R104,R416	KOA (R)	RK73B1ELTP472J
38	0 1/10W 5% 0402	R42-R45,R50,R112,R117-R120,R194,R198,R282,R286,R304,R321,R331-R333,R336,R338,R339,R362-R366,R388,R396,R398,R430,R447,R486,R488,R490,R492,R494,R496	DIGI-KEY (R)	P0.0JTR-ND
1	22 1/10W 5% 0402	R202	DIGI-KEY (R)	P22JTR-ND
15	33 1/16W 5% 0402	R36,R38,R40,R121,R147-R150,R265,R272,R335,R349,R356,R419,R421	VISHAY (R)	CRCW040233ROJNED
1	150UF 10V 10% D TANT-LOW-ESR	CT16	DIGI-KEY (R)	478-3321-2-ND
1	107.0 1/10W 1% 0805	R204	VISHAY-DAL (R)	CRCW0805107RFKEA

Qty	Description	Reference Designator	Manufacturer	Part Number
1	249.0 1/10W 1% 0805	R203	VISHAY (R)	CRCW0805249RFKEA
19	1UF 16V 10% 0603 X5R	C54-C57,C59,C60,C62,C64-C67,C76-C79,C85,C276,C408,C411	TDK	C1608X5R1C105K080AA
1	4.7UF 25V 20% 0805 X5R	C394	AVX CORPOR (R)	0805ZD475KAT2A
1	4.7UF 6.3V 20% 0603 X5R	C38	MURATA (R)	GRM188R60J475KE19D
2	330 1/10W 5% 0603	R99,R100	DIGI-KEY (R)	541-330GTR-ND
2	1M 1/10W 5% 0603	R47,R387	KOA (R)	RK73B1JTTDD105J
1	130.0K 1/16W 1% 0603	R444	VISHAY (R)	CRCW0603130KFKEA
2	10.0K 1/16W 1% 0603	R201,R443	KOA (R)	RK73H1JTTDD1002F
2	1K 1/10W 5% 0603	R87,R88	KOA (R)	RK73B1JTTDD102J
8	237.0 1/10W 1% 0603	R211,R214,R219,R222,R227,R230,R235,R238	PANASONIC (R)	ERJ-3EKF2370V
4	750.0K 1/10W 1% 0603	R213,R221,R229,R237	KOA (R)	RK73H1JTTDD7503F
5	11.0K 1/10W 1% 0603	R209,R217,R225,R233,R337	KOA (R)	RK73H1JTTD1102F
8	5.49K 1/10W 1% 0603	R207,R212,R215,R220,R223,R228,R231,R236	VISHAY (R)	CRCW06035K49FNEA
2	49.9K 1/10W 1% 0603	R189,R190	KOA (R)	RK73H1JTTDD4992F
9	5.76K 1/10W 1% 0603	R208,R210,R216,R218,R224,R226,R232,R234,R325	KOA (R)	RK73H1JTTDD5761F
8	100PF 50V 5% 0603 NPO	C213,C217,C220,C224,C227,C231,C234,C238	DIGI-KEY (R)	478-1175-2-ND
8	1000PF 50V 5% 0603 X7R	C215,C216,C222,C223,C229,C230,C236,C237	KEMET Corporati	C0603C102J5RAC7867
8	680PF 50V 5% 0603 NPO	C211,C214,C218,C221,C225,C228,C232,C235	MURATA (R)	GRM1885C1H681JA01D
1	75.0 1/10W 1% 0603	R200	YAGEO (R)	RT0603FRE0775RL
20	1UF 6.3V 20% 0402 X5R	C154,C155,C183,C251,C252,C258,C259,C290,C291,C298,C299,C306-C308,C392,C397,C398,C403,C404,C406	Murata	GRM153R60J105ME15D
3	100 1/16W 5% 0402	R270,R271,R433	PANASONIC (R)	ERJ-2GEJ101X
2	390PF 25V 5% 0603 NPO	C96,C136	KOA (R)	NPO0603HTTD391J
2	5600PF 16V 5% 0805 NPO	C95,C135	KOA (R)	X7R0805HTTD562J

Qty	Description	Reference Designator	Manufacturer	Part Number
1	15.0K 1/16W 1% 0603	R199	KOA (R)	RK73H1JTTDD1502F
20	10UF 10V 10% 0805 X5R	C53,C58,C61,C88,C90,C102,C104,C106-C109,C114,C116,C128,C130,C133,C134,C414,C422,C424	MURATA (R)	GRM21BR61A106KE19L
1	61.9K 1/16W 1% 0603	R441	DIGI-KEY (R)	P61.9KHTR-ND
4	0.051 1/2W 1% 1206	R288,R289,R291,R389	ROHM	UCR18EVHFSR051
1	10UF 16V 10% 1210 X5R	C419	TAIYO YUDE (R)	EMK325BJ106KN-T
2	1000PF 50V 5% 1206	C418,C420	AVX CORPOR (R)	12065A102JAT2A
2	5A MBR540T3G SMC	D14,D16	DIGI-KEY (R)	MBRS540T3GOSCT-ND
1	VARISTOR V5.5MLA 30A 0603	R359	LITTELFUSE (R)	V5.5MLA0603H
1	PTC 0.5A 1206	R400	LITTELFUSE (R)	1206L050YR
13	330.0 1/16W 1% 0402	R5,R48,R49,R239-R242,R251-R255,R258	VISHAY (R)	CRCW0402330RFKED
1	47.0K 1/16W 1% 0402	R68	ROHM	MCR01MZPF4702
2	3.01K 1/16W 1% 0402	R26,R435	DIGI-KEY	RHM3.01KCDTR-ND
9	1.0K 1/10W 1% 0402	R2,R3,R8,R9,R107,R115,R128,R142,R368	PANASONIC (R)	ERJ-2RKF1001X
2	10.0K 1/16W 1% 0402	R334,R397	DIGI-KEY (R)	541-10.0KLCT-ND
1	1.50K 1/16W 1% 0402	R25	DIGI-KEY (R)	P1.50KLCT-ND
6	680 1/16W 1% 0402	R62,R63,R101,R342-R344	VISHAY (R)	MCS04020C6800FE000
20	100K 1/16W 5% 0402	R108-R110,R137-R139,R281,R284,R322,R357,R358,R392,R401-R404,R417,R440,R449,R450	DIGI-KEY (R)	541-100KJTR-ND
1	15PF 50V 5% 0402 NPO	C407	KEMET (R)	C0402C150J5GACTU
1	1.0 1/16W 1% 0402	R455	VISHAY-DAL (R)	CRCW04021R00FNED
1	22UF 16V 10% 1210 X5R	C48	TAIYO YUDE (R)	EMK325BJ226KM-T
1	1.24K 1/16W 1% 0603	R86	Panasonic (R)	P1.24KHTR-ND
6	18PF 50V 5% 0402 NPO	C22,C25,C26,C28-C30	Murata	GRM1555C1H180JA01D

Qty	Description	Reference Designator	Manufacturer	Part Number
1	33 1/16W 5% RNS003	RN6	PANASONIC (R)	EXB-2HV330JV
7	33 1/32W 5% RNS005	RN1-RN5,RN7,RN8	PANASONIC (R)	EXB-28V330JX
2	0.01UF 25V 10% 0402 X7R	C36,C40	KEMET (R)	C0402C103K3RACTU
2	100.0 1/16W 1% 0402	R10,R122	VISHAY (R)	CRCW0402100RFKED
6	100PF 50V 5% 0402 COG	C74,C75,C80-C82,C384	TDK	CGA2B2COG1H101J050BA
1	2.43K 1/16W 1% 0402	R328	DIGI-KEY	541-2.43KLCT-ND
16	2.2K 1/10W 5% 0402	R13-R18,R23,R129-R136,R327	PANASONIC (R)	ERJ-2GEJ222X
4	GREEN LED_0603	LED4,LED6,LED9,LED18	LUMEX	SML-LX0603GW-TR
2	4700PF 2A FIL_NFE61PT	FER30,FER33	MURATA (R)	NFE61PT472C1H9L
4	10UF 16V 10% 0805 X5R	C260,C262,C264,C266	MURATA (R)	GRM21BR61C106KE15L
3	499.0 1/10W 1% 0402	R96,R98,R257	DIGI-KEY (R)	P499LTR-ND
2	22PF 50V 5% 0402 NPO	C51,C52	KEMET (R)	C0402C220J5GACTU
2	2.0K 1/10W 1% 0402	R326,R448	PANASONIC (R)	ERJ-2RKF2001X
5	0.1UF 16V 10% 0402 X7R	C35,C37,C39,C208,C209	DIGI-KEY (R)	587-1451-2-ND
2	15KV ESD7004 UDFN10	D5,D13	ON SEMICON (R)	ESD7004MUTAG
1	15KV ESDA6V1SC SOT95P280-6N	D4	ST MICROEL (R)	ESDA6V1SC6
2	300.0 1/10W 1% 0402	R317,R318	DIGI KEY	P300LTR-ND
2	60.4K 1/10W 1% 0603	R60,R61	DIGI-KEY (R)	311-60.4KHRTR-ND
1	22UF 6.3V 20% 0805 X5R	C63	TDK (R)	C2012X5R0J226M125AC
2	32.4K 1/10W 1% 0402	R287,R297	DIGI-KEY (R)	P32.4KLTR-ND
1	562.0 1/16W 1% 0402	R114	PANASONIC (R)	ERJ-2RKF5620X
1	390PF 50V 5% 0402 NPO	C111	MURATA (R)	GRM1555C1H391JA01D
2	10PF 50V 5% 0402 NPO	C399,C400	DIGI-KEY (R)	399-1011-2-ND
2	10.2K 1/16W 1% 0402	R429,R442	VISHAY-DAL (R)	CRCW040210K2FKED

Qty	Description	Reference Designator	Manufacturer	Part Number
1	10UF 50V 20% SMD	CT1	PANASONIC (R)	EEE-FC1H100P
1	4.7UH 30% SMD	L5	WURTH ELEC (R)	7440530047
3	RED LED_0603	LED1,LED19,LED22	OSRAM OPTO (R)	LS Q976-NR-1
12	YELLOW LED_0603	LED2,LED3,LED5,LED7,LED10-LED17	OSRAM	LY L296-Q2R2-26-Z
2	10UF 6.3V 20% 0603 X5R	C19,C402	MURATA	GRM188R60J106ME47D
12	475 1/8W 1% 0805	R165,R167,R169,R171,R173,R175,R177,R179,R181,R183,R185,R187	DIGI-KEY (R)	P475CTR-ND
2	150PF 50V 5% 0402 NPO	C49,C50	DIGI-KEY (R)	490-3229-2-ND
1	10 1/10W 1% 0402	R399	DIGI-KEY (R)	P10.0LTR-ND
4	4700PF 50V 10% 0402 X7R	C47,C156,C261,C263	DIGI-KEY (R)	399-3072-2-ND
12	49.9K 1/16W 1% 0402	R166,R168,R170,R172,R174,R176,R178,R180,R182,R184,R186,R188	VISHAY (R)	CRCW040249K9FKED
3	10UF 6.3V 20% 0402 X5R	C284,C300,C315	DIGI-KEY (R)	445-8920-1-ND
1	0.1UF 35V 10% 0402 X7R	C46	TDK (R)	CGA2B3X7R1V104K050BB
1	53.6K 1/16W 1% 0402	R428	VISHAY-DAL (R)	CRCW040253K6FKED
8	0.01UF 50V 10% 0402 X7R	C158,C256,C272,C285,C296,C302,C310,C317	MURATA (R)	GCM155R71H103KA55D
1	180.0K 1/16W 1% 0402	R58	DIGI-KEY (R)	541-180KLTR-ND
1	5600PF 25V 10% 0402 X7R	C112	MURATA (R)	GRM155R71E562KA01D
12	2700PF 50V 5% 0805 COG	C186-C197	TDK (R)	C2012C0G1H272J060AA
1	2.2UF 100V 10% 1210 X7R	C275	Kemet (R)	C1210C225K1RACTU
1	47UF 16V 20% 1210 X5R	C390	Taiyo Yuden	EMK325BJ476MM-T
1	1.8K 1/10W 5% 0402	R290	DIGI-KEY	P1.8KJTR-ND
2	39PF 50V 5% 0402 NPO	C292,C293	SAMSUNG (R)	CL05C390JB5NUNC
4	0.47UF 50V 10% 0603 X5R	C98-C101	TAIYO YUDE (R)	UMK107ABJ474KA-T
4	68PF 50V 5% 0402 NPO	C70-C73	DIGI-KEY (R)	490-5876-2-ND

Qty	Description	Reference Designator	Manufacturer	Part Number
1	26.7K 1/16W 1% 0402	R445	DIGI-KEY	541-26.7KLTR-ND
1	28 1/10W 1% 0402	R85	DIGI-KEY	P28.0LTR-ND
1	3.74K 1/16W 1% 0402	R299	PANASONIC (R)	ERJ-2RKF3741X
4	4.02 1/16W 1% 0402	R89-R92	VISHAY (R)	CRCW04024R02FKED
4	45.3 1/10W 1% 0402	R93,R94,R105,R106	PANASONIC (R)	ERJ-2RKF45R3X
2	619 1/10W 1% 0402	R20,R21	PANASONIC (R)	ERJ-2RKF6190X
3	5MA MM5Z3V3T1G MM5Z3V3T1G _ZENER	D15,D17,D18	DIGI-KEY (R)	MM5Z3V3T1GOSTR-ND
1	15KV ESDA5V3SC6 SOT23-6	D12	ST MICROEL (R)	ESDA5V3SC6
1	34 1/10W 1% 0402	R1	PANASONIC (R)	ERJ-2RKF34R0X
1	240 1/10W 1% 0402	R4	DIGI-KEY (R)	P240LTR-ND
1	3000PF 50V 5% 0603 NPO	C267	DIGI-KEY (R)	490-6384-2-ND
6	47UF 6.3V 20% 0805 X5R	C268-C271,C273,C274	TAIYO YUDE (R)	JMK212BJ476MG-T
2	3A PESD1CAN SMT	D1,D2	NXP (PHILI (R)	PESD1CAN,215
2	510 .2A SMT	FER1,FER2	DIGI-KEY (R)	445-3958-2-ND
1	3.3UH 20% SMT	L6	COILCRAFT (R)	XAL4030-332ME
1	2.2UH 20% SMT	L8	COILCRAFT	XAL5030-222MEC
2	105.0 1/16W 1% 0402	R11,R12	VISHAY (R)	CRCW0402105RFKED
1	31.6K 1/10W 1% 0402	R279	PANASONIC (R)	ERJ-2RKF3162X
3	22K 1/10W 1% 0402	R300,R301,R393	DIGI-KEY (R)	P22.0KLTR-ND
1	8.66K 1/10W 1% 0402	R303	DIGI-KEY (R)	P8.66KLTR-ND
1	5.1K 1/10W 1% 0402	R283	DIGI-KEY (R)	P5.10KLTR-ND
1	4.3K 1/10W 1% 0402	R280	DIGI-KEY (R)	P4.30KLTR-ND
1	1.0UH 20% SMT	L7	COILCRAFT (R)	XAL5030-102MEC
4	470 1A 0603	FER7,FER10-FER12	MURATA (R)	BLM18PG471SN1D

Qty	Description	Reference Designator	Manufacturer	Part Number
1	200 100MA CHOKE_ACT45L	FER31	TDK	ACT45L-201-2P
4	220NH 2% 0603	L1-L4	COILCRAFT	0603HP-R22XGLU
2	600 1.5A 0603	FER8,FER9	LAIRD (R)	MI1206K601R-10
2	470 2A 1806	FER5,FER6	MURATA (R)	BLM41PG471SN1L
2	18.2 1/10W 1% 0402	R95,R97	PANASONIC (R)	ERJ-2RKF18R2X
1	33UF 6.3V 20% 1206 X5R	C405	DIGI-KEY (R)	445-4060-2-ND
1	6.8UH 30% SMD	L12	BOURNS (R)	SRN8040-6R8Y
1	5A CDBC540-G DO214AB	D11	COMCHIP TE (R)	CDBC540-G
1	47UF 10V 20% SMD POLYMER	CT17	UNITED CHE (R)	APXE100ARA470ME61G
1	30A GSOT12 SOT23-3	D3	DIGI-KEY	GSOT12-E3-08TR-ND
1	0.1 1/2W 1% 1206	R292	DIGI-KEY	CSR1206FTR100TR-ND
4	390.0 1/16W 1% 0402	R319,R320,R345,R346	DIGI-KEY	311-390LRTR-ND

