

	Qty	Reference	Part Description	Manufacturer / Part #
REQUIRED CIRCUIT COMPONENTS:				
1	1	COUT1	CAP, 7343 220uF 20% 4V POSCAP	SANYO 4TPE220MF
2	1	COUT2	CAP, 7343 68uF 20% 10V POSCAP	SANYO 10TPC68M
3	4	C1,C10,C16,C23	CAP, 0603 0.1uF 10% 25V X7R	AVX 06033C104KAT
4	1	C2	CAP, 0603 10pF 5% 50V NPO	AVX 06035A100JAT
5	1	C3	CAP, 0603 22pF 5% 25V NPO	AVX 06033A220JAT
6	1	C4	CAP, 0603 4700pF 25V20% X7R	AVX 06033C472MAT
7	1	C5	CAP, 1210 100uF 20% 6.3V X5R	TAIYO YUDEN JMK325BJ107MM-T
8	2	C6,C18	CAP, 0603 1000pF 10% 25V X7R	AVX 06033C102KAT
9	2	C7,C17	CAP, 1210 4.7uF 10% 50V X7R	KEMET C1210C475K5RAC7533
10	2	C11,C22	CAP, 0805 4.7uF 10% 10V X5R	KEMET C0805C475K8PAC7533
11	1	C12	CAP, 0603 0.1uF 10% 50V X7R	AVX 06035C104KAT2A
12	1	C13	CAP, 47uF 20% 50V ELECTROLYTIC	SANYO 50CE47BS
13	1	C14	CAP, 0603 47pF 5% 25V NPO	AVX 06033A470JAT2A
14	1	C15	CAP, 0603 3300pF 5% 50V X7R	AVX 06035C332JAT2A
15	1	C19	CAP, 0603 2.2uF 10% 10V X5R	MURATA GRM188R61A225KE34D
16	1	C20	CAP, 1210 10uF 10% 16V X5R	TAIYO YUDEN EMK325BJ106KN-T
17	2	D2,D3	DIODE, SCHOTTKY SOD323	CENTRAL CMDSH-4E
18	1	L1	IND, 3.2uH	SUMIDA CDEP105NP-3R2MC-88
19	4	Q1,Q2,Q3,Q4	XSTR, N-CHANNEL MOSFET	INFINEON BSZ097N04LS
20	1	R1	RES, 0603 200K OHMS 5% 1/10W	YAGEO RC0603JR-07200KL
21	1	R2	RES, 0603 35.7K OHMS 1% 1/10W	YAGEO RC0603FR-0735K7L
22	1	R3	RES, 0603 11.5K OHMS 1% 1/10W	YAGEO RC0603FR-0711K5L
23	1	R4	RES, 0603 57.6K OHMS 1% 1/10W	YAGEO RC0603FR-0757K6L
24	1	R5	RES, 0603 182K OHMS 1% 1/10W	YAGEO RC0603FR-07182KL
25	1	R10	RES, 2010 0.005 OHMS 5% 1W	TT ELECTRONICS LRC-LRF2010LF-01-R005J
26	1	R11	RES, 0603 8.2K OHMS 1% 1/10W	YAGEO RC0603FR-078K2J
27	2	R13,R15	RES, 0603 2.2 OHMS 5% 1/10W	YAGEO RC0603FR-072R2L
28	1	R16	RES, 0603 15K OHMS 1% 1/10W	YAGEO RC0603FR-0715KL
29	1	R17	RES, 2010 0.008 OHMS 5% 1W	TT ELECTRONICS LRC-LRF2010LF-01-R008G
30	1	R18	RES, 0603 102K OHMS 1% 1/10W	YAGEO RC0603FR-07102KL

31	2	R19, R24	RES, 0603 976K OHMS 1% 1/10W	YAGEO RC0603FR-07976KL
32	1	R25	RES, 0603 10K OHMS 1% 1/10W	YAGEO RC0603FR-0710KL
33	1	R27	RES, 0603 100k OHMS 5% 1/10W	YAGEO RC0603FR-07100KL
34	1	R35	RES, 0603 66.5K OHMS 1% 1/10W	VISHAY CRCW060366K5FKEA
35	1	R37	RES, 0603 12.7K OHMS 1% 1/10W	VISHAY CRCW060312K7FKEA
36	1	U1	IC, STEP-DOWN CONTROLLER	LINEAR TECH. LTC3858EGN-1
ADDITIONAL DEMO BOARD CIRCUIT COMPONENTS:				
1	0	COUT3,COUT4	CAP, 7343 220uF 20% 4V POSCAP OPTION	SANYO 4TPE220MF OPTION
2	0	C21,C26,C27,C28,C29	CAP, 0603 OPTION	OPTION
3	0	C24,C25	CAP, 1210 4.7uF 10% 50V X7R OPTION	KEMET C1210C475K5RAC7533 OPTION
4	0	Q5,Q6,Q7,Q8	XSTR, N-CHANNEL MOSFET OPTION	VISHAY Si7848BDP OPTION
5	0	R26,R28,R29-R34,R36,R38	RES, 0603 OPTION	OPTION
HARDWARE-FOR DEMO BOARD ONLY:				
1	9	R6,R7,R8,R9,R14,R20-R23,	RES, 0603 0 OHM JUMPER	YAGEO RC0603FR-070RL
2	1	JP2	Header, 3X2 2mm	SAMTEC TMM-103-02-L-D
3	4	JP3,JP4,JP5,JP6	HEADER,3PIN, 2mm	SAMTEC TMM-103-02-L-S
4	6	J1,J2,J3,J4,J5,J6	JACK, BANANA	KEYSTONE 575-4
5	7	E1,E2,E3,E4,E9,E10,E15	TURRET	MILL MAX 2308-2-00-80-00-00-07-0
6	6	E5,E6,E11,E12,E13,E14	TURRET	MILL-MAX 2501-2-00-80-00-00-07-0
7	5	JP2-JP6	SHUNT, 2mm	SAMTEC 2SN-BK-G
8	4		STANDOFF, SNAP ON	KEYSTONE_8833