



IMPEDANCE STANDARDS

• CAPACITANCE • INDUCTANCE • RESISTANCE

PRECISION CAPACITOR

Type 1422

- variable air capacitor
- stability: better than 0.02% full scale per year
- settable to 40 ppm
- low temperature coefficient, low losses
- wide selection to suit needs





Panel and interior views of 1422-D Precision Capacitor.

The 1422 is a stable and precise variable air capacitor intended for use as a continuously adjustable standard of capacitance.

One of the most important applications is in ac bridge measurements, either as a built-in standard or as an external standard for substitution measurements. It is available in a variety of ranges, terminal configurations, and scale arrangements to permit selection of precisely the required characteristics.

TWO-TERMINAL

The 1422-D is a dual-range, two-terminal capacitor, direct reading in total capacitance at the terminals. For high-frequency use, the 1422-N, similar to the high-capacitance section of the 1422-D, is designed to have low residual inductance and resistance.

For convenience in making substitution measurements, two 1422's have scales reading in capacitance removed, i.e., the capacitance is maximum at the zero reading. These, the 1422-MD and 1422-ME, are also dual-range, two-terminal capacitors.

THREE-TERMINAL

The 1422-CB, -CC, -CL, -CD, and -CE are three-terminal capacitors with shielded coaxial terminals for use in three-terminal measurements. The calibrated direct capacitance is independent of terminal capacitances to ground, and losses are very low. The 1422-CL has approximately the same maximum capacitance as the -CC, but

with more constant and much lower terminal capacitances, so that it can be used in measurement circuits where high capacitance to guard can not be tolerated.

CONSTRUCTION

The capacitor assembly is mounted in a cast frame for rigidity. This frame and other critical parts are made of aluminum alloys selected to give the strength of brass with the lightness of aluminum. The plates of most models are also aluminum, so that all parts have the same temperature coefficient of linear expansion.

A worm drive is used to obtain high precision of setting. To avoid eccentricity, the shaft and the worm are accurately machined as one piece. The worm and worm wheel are also lapped into each other to improve smoothness. The dial end of the worm shaft runs in a self-aligning ball bearing, while the other end is supported by an adjustable spring mounting, which gives positive longitudinal anchoring to the worm shaft through the use of a pair of sealed, self-lubricating, preloaded ball bearings. Similar pairs of preloaded ball bearings provide positive and invariant axial location for the main or rotor shaft. Electrical connection to the rotor is made by means of a silver-alloy brush bearing on a silver-overlay drum to assure a low-noise electrical contact.

Stator insulation in all models is a cross-linked thermosetting modified polystyrene having low dielectric losses and very high insulation resistance. Rotor insulation, where used (Types 1422-CB, -CL, and -N), is grade L-4 steatite, silicone treated.

specifications

Initial Accuracy: See table. The errors tabulated are possible errors, i.e., the sum of error contributions from setting, adjustment, calibration, interpolation, and standards. When the capacitor is in its normal position with the panel horizontal, the actual errors are almost always smaller. The accuracy is improved when the readings are corrected using the 12 calibrated values of capacitance given on the correction chart on the capacitor panel and interpolating linearly between calibrated points. Better accuracy can be obtained from a precision calibration of approximately 100 points on the capacitor dial, which permits correction for slight residual eccentricities of the worm drive and requires interpolation over only short intervals. This precision calibration

is available for all models at an extra charge. Models so calibrated are listed with the additional suffix letter, P, in the type number. A plastic-enclosed certificate of calibration is supplied, giving corrections to one more figure than the tabulated accuracy.

Stability: The capacitance change with time is less than 1 scale division (0.02% of full scale) per year. The long-term accuracy can be estimated from the stability and the initial accuracy specifications.

Calibration: The measured values are obtained by comparison at 1 kHz, with working standards whose absolute values are known to an accuracy of $\pm (0.01\% + 0.0001 \text{ pF})$. Each comparison is

made to a precision better than $\pm 0.01\%$. The values of the working standards are determined and maintained in terms of reference standards periodically calibrated by the National Bureau of Standards.

The indicated value of total capacitance of a two-terminal capacitor is the capacitance added when the 1422 Capacitor is plugged into a 777-Q3 Adaptor. The uncertainty of this method of connection is approx ±0.03 pF.*

Resolution: Dial can be read and set to 1/5 of a small division. The backlash is less than 1/5 small division, corresponding to 0.004% of full-scale value. If the desired setting is always approached in the direction of increasing scale reading, no error from this cause will result.

Temperature Coefficient: Approx +20 ppm/°C, for small temperature changes.

Residual Parameters: See table. The series resistance varies as the square root of the frequency above 100 kHz. Its effect is negligible below this frequency.


Frequency Characteristic: See curves for two-terminal models. The resonance frequency for the -CB and -CC models is approximately 20 MHz; for the -CD model, 60 MHz for each section; -CL, 40 MHz.

Dissipation Factor: The losses in the two-terminal capacitors are primarily in the stator supports, which are of low-loss polystyrene (DC = 0.01×10^{-12}).

The very small dissipation factor of the direct capacitance of the three-terminal capacitors is difficult to measure and is estimated to be not greater than 20 \times 10⁻⁶ for -CB and -CL, and 10 \times 10⁻⁶ for -CC, -CD, and -CE.

Insulation Resistance: Under standard conditions (23°C, less than 50% RH), greater than 10¹² ohms.

Max Voltage: All models, 1000 V, peak.



Variation with frequency of effective capacitance and dissipation factor per pF of capacitance for two-terminal 1422 Precision Capacitors.

Terminals: Jack-top binding posts are provided on 2-terminal models; standard ¼-inch spacing is used. The rotor terminal is connected to the panel and shield. Locking GR874 Coaxial Connectors are used on three-terminal models.

Accessories Required: For connection to 3-terminal models, 2 GR874 Patch Cords or equivalent.

 $\begin{tabular}{lll} Accessories Available: 777-Q3 Adaptor (see Calibration above), for two-terminal units. \end{tabular}$

Mounting: Lab-Bench Cabinet.

Dimensions (width x height x depth): $9\frac{1}{2}$ x 7 x $8\frac{1}{2}$ in. (245 x 180 x 220 mm).

Weight: Net, 104/2 to 124/2 lb (4.8 to 5.7 kg), depending on model; shipping, all models, 15 lb (7 kg).

				Tv	vo-Termi	nal									
				RF		Reads Ca Rem	pacitan loved	ce				Three-Terminal			
TYPE 142	2	-	D	-N	-N	ID	-М	E	-CB	-cc	-CL	-c	D	-(CE
CAPACITANCE	Min	100	35	100	0	0	0	0	50	5	10	0.5	0.05	0.05	0.005
RANGE, pF	Max	1150	115	1150	1050	105	105	10.5	1100	110	110	11	1.1	1.1	0.11
SCALE, pF/Division:		0.2	0.02	0.2	0.2	0.02	0.02	0.002	0.2	0.02	0.02	0.002	0.0002	0.0002	0.00002
INITIAL ACCURACY: ± F Direct-Reading (Adjus Total Capacitance		0.6*	0.1*	0.6*	Diff	erence	s from	Zero	0.6	0.15	0.1	0.04	0.008	0.008	0.0016
Capacitance Differe	nce	1.2	0.2	1.2	1	0.2	0.2	0.05	1.2	0.3	0.2	0.08	0.016	0.016	0.0032
With Corrections from Chart (supplied): Total Capacitance	Calibration	0.3*	0.04*	0.3*					0.3	0.04	0.04	0.01	0.002	0.002	0.0004
Capacitance Differe	ncet	0.6	0.08	0.6	0.6	0.08	80.0	0.02	0.6	0.08	0.08	0.02	0.004	0.004	0.0008
With Corrections from Calibration (extra cha Total Capacitance		0.1*	0.01*	0.1*	1		. 1		0.1	0.01	0.01	0.001	0.0002	0.0002	0.00004
Capacitance Differe	ncet	0.2	0.02	0.2	0.2	0.02	0.02	0.004	0.2	0.02	0.02	0.002	0.0004	0.0004	0.00008
RESIDUALS (typical val Series Inductance, μΗ		0.06	0.10	0.032	0.06	0.10	0.06	0.10	0.14	0.17	0.13	0.17	0.17	0.17	0.17
Series Resistance, oh	ms at 1 MHz	0.04	0.05	0.012	0.04	0.05	0.04	0.05	0.1		0.1				
				h termi			min	scale	36	850	34	98	25	37	28
Tamasian I Cananitanan			nig	n termi	nai to c	ase	max	scale	35	560	33	74	23	35	28
Terminal Capacitance	, pr:						min	scale	58	920	58	117	115	81	81
			lov	v termir	iai to c	ase	max	scale	53	600	55	92	93	67	67
Capacitance at Zero S	cale Setting,	pF:			1140	135	145	35							

^{*} Total capacitance is the capacitance added when the capacitor is plugged into a 777-Q3 Adaptor. † Divide error by 2 when one setting is made at a calibrated point.

Catalog Number	Description	Price in USA	Catalog Number	Description	Price in USA
1422-9904 1422-9913 1422-9955 1422-9880 1422-9903 1422-9508 1422-9508 1422-9580	Precision Capacitors with precision calibration 1422-DP 1422-MDP 1422-MEP 1422-NP 1422-CBP 1422-CCP 1422-CLP 1422-CDP 1422-CEP 1422-CEP	\$620.00 625.00 620.00 565.00 550.00 535.00 535.00 560.00	1422-9704 1422-9854 1422-9855 1422-9714 1422-9916 1422-9809 1422-9823 1422-9823 1422-9833 0777-9803	with standard calibration 1422-D 1422-MD 1422-ME 1422-N 1422-CB 1422-CC 1422-CL 1422-CD 1422-CE 777-Q3 Adaptor	\$510.00 515.00 510.00 495.00 480.00 465.00 465.00 450.00 510.00

^{*} John F. Hersh, "A Close Look at Connection Errors in Capacitance Measurements," General Radio Experimenter, July 1959.


REFERENCE STANDARD CAPACITOR

Type 1404

- 10, 100, 1000 pF
- 20 ppm/year stability
- 3-terminal, coaxial connections
- hermetically sealed in dry nitrogen



These capacitors have been designed as primary reference standards of capacitance with which working standards can be compared. The 1615-A Capacitance Bridge is particularly well suited for this purpose and can be conveniently used to calibrate accurately a wide range of working standards-in terms of a 1404 Reference Standard Capacitor. A single 1000- or 100-picofarad standard is also the only standard necessary to calibrate the bridge itself.



Equivalent circuit showing direct capacitance, $C_{\rm D}$, and average values of residual inductance, L, and terminal capacitances, $C_{\rm H}$ and $C_{\rm L}$. $C_{\rm D}=1000$ pF for 1404-A, 100 pF for 1404-B, and 10 pF for 1404-C.

In combination with an accurately known external resistor, this capacitor becomes a standard of dissipation factor.

All critical parts of the plate assembly are made of Invar for stability and low temperature coefficient. After heat cycling and adjustment, the assembly is mounted in a heavy brass container, which, after evacuation, is filled with dry nitrogen under pressure slightly above atmospheric and sealed. The container is mounted on an aluminum panel and protected by an outer aluminum case. Each capacitor is subjected to a series of temperature cycles to determine hysteresis and temperature coefficients and to stabilize the capacitance.

Two locking GR874 Coaxial Connectors are used as terminals. The outer shell of one is connected to the case, but the outer shell of the other is left unconnected to permit the capacitor to be used with an external resistor as a dissipation-factor standard.

- See GR Experimenter for Aug 1963 and Aug 1966.

specifications

Calibration: A certificate of calibration is supplied with each capacitor, giving the measured direct capacitance at 1 kHz and at $23^{\circ} \pm 1^{\circ}$ C. The measured value is obtained by a comparison to a precision better than ± 1 ppm with working standards whose absolute values are known to an accuracy of ± 20 ppm, determined and maintained in terms of reference standards periodically measured by the National Bureau of Standards.

Adjustment Accuracy: The capacitance is adjusted before calibration with an accuracy of ± 5 ppm to a capacitance about 5 ppm above the nominal value relative to the capacitance unit maintained by the General Radio reference standards.

Stability: Long-term drift is less than 20 parts per million per year. Maximum change with orientation is 10 ppm and is completely reversible.

Temperature Coefficient of Capacitance: $2\pm2~ppm/^{\circ}C$ for 1404-A and -B, $5\pm2~ppm/^{\circ}C$ for 1404-C, from $-20^{\circ}C$ to $+65^{\circ}C$. A measured value with an accuracy of $\pm1~ppm/^{\circ}C$ is given on the certificate.

Temperature Cycling: For temperature cycling over range from -20° C to $+65^{\circ}$ C, hysteresis (retraceable) is less than 20 ppm at 23°C.

Dissipation Factor: Less than 10-5 at 1 kHz.

Residual Impedances: See equivalent circuit for typical values of internal series inductances and terminal capacitances.

Max Voltage: 750 V.

Terminals: Two locking GR874 coaxial connectors; easily convertible to other types of connectors by attachment of locking adaptors. Outer shell of one connector is ungrounded to permit capacitor to be used with external resistor as a dissipation-factor standard.

Accessories Required: For connection to 1615-A Capacitance Bridge, 2 Type 874-R20A or 874-R22LA Patch Cords.

Dimensions (width x height x depth): 63% x 65% x 8 in. (175 x 170 x 205 mm).

Weight: Net, 81/2 lb (3.9 kg); shipping, 14 lb (6.5 kg).

Catalog Number				
	Reference Standard Capacitor			
1404-9701	1404-A, 1000 pF	\$225.00		
1404-9702	1404-B, 100 pF	225.00		
1404-9703	1404-C, 10 pF	225.00		



- 0.001 to 1 μF
- ±0.01%/year stability
- calibration accuracy ±0.02%
- two- and three-terminal calibration provided

STANDARD CAPACITOR

Type 1409




The 1409 Standard Capacitors are fixed mica capacitors of very high stability for use as two- or three-terminal reference or working standards in the laboratory.


Typical capacitors, observed over more than ten years, have shown random fluctuations of less than $\pm 0.01\%$ in measured capacitance with no evidence of systematic drift.

These capacitor units consist of a silvered-mica and foil pile, spring-held in a heavy metal clamping structure

for mechanical stability. The units are selected for low dissipation factor and are stabilized by heat cycling. They are housed, with silica gel to provide continuous desiccation, in cast aluminum cases, sealed with high-temperature potting wax. A well is provided in the wall of the case for the insertion of a dial-type thermometer. Three jack-top binding posts are provided on the top of the case and removable plugs on the bottom, for convenient parallel connection without error.



(Left) Change in capacitance as a function of frequency for typical Type 1409 Capacitors. The 1-kHz value on the plot should be used as a basis of reference in estimating frequency errors. (Right) Dissipation factor as a function of frequency.



specifications

Adjustment Accuracy: Within $\pm 0.05\%$ of the nominal capacitance value (two-terminal) marked on the case. Accuracy is guaranteed for two years under the terms of our standard warranty if the capacitor has not been damaged by excessive current or voltage.

Calibration: A certificate of calibration is supplied with each unit, giving both two- and three-terminal measured capacitances at $1\,$ kHz and at a specified temperature. The measured value is the capacitance added when the standard is plugged directly into General Radio binding posts. This value is obtained by comparison, to a precision better than $\pm 0.01\%$, with working standards whose absolute values are known to an accuracy typically $\pm 0.01\%$, determined and maintained in terms of reference standards periodically calibrated by the National Bureau of Standards.

Stability: Capacitance change is less than 0.01% per year.

Temperature Coefficient of Capacitance: $+35\pm10$ ppm per degree between 10° and 70°C.

Dissipation Factor: Less than 0.0003 at 1 kHz and 23°C (see curves). Measured dissipation factor at 1 kHz is stated in the certificate to an accuracy of ± 0.00005 .

Series Inductance: Typically 0.050 μ H for 1409-F through -M, 0.055 μ H for -R through -X, and 0.070 μ H for 1409-Y.

Series Resistance at 1 MHz: 0.02 ohm, except for 1409-Y, which is 0.03 ohm.

Frequency Characteristics: See curves. Series resistance varies as the square root of the frequency for frequencies above 100 kHz.

Approx Terminal Capacitance: From H terminal to case (G), 12 to

50 pF. From L terminal (outside foils of capacitor) to case, 300 to 1300 pF.


Leakage Resistance: 5000 ohm-farads or 100 $G\Omega_{\mbox{\scriptsize N}}$ whichever is the lesser.

Max Voltage: 500 V pk below the limiting frequencies tabulated below. At high frequencies the allowable voltage is approx inversely proportional to frequency. These limits correspond to a temperature rise of 40°C for power dissipations of 5, 6, and 7.5 W for the small, medium, and large cases, respectively.

Dimensions (width x height x depth): 1409-Y, $3\frac{1}{4} \times 5\frac{5}{8} \times 2\frac{1}{6}$ in. (85 x 145 x 70 mm); 1409-Y, $3\frac{1}{4} \times 4 \times 2\frac{1}{6}$ in. (85 x 105 x 70 mm); others, $3\frac{1}{4} \times 4 \times 2$ in. (85 x 105 x 50 mm).

Weight: Net, 11/4 lb (0.6 kg); shipping, 4 lb (1.9 kg). Add approx 1/2 lb (0.2 kg) for 1409-X, and approx 1 lb (2.2 kg) for 1409-Y.

Catalog Number	Туре	Nominal Capaci- tance μF	Frequency Limit for Max Volts	Price in USA
1409-9706	1409-F	0.001	4.7 MHz	\$ 55.00
1409-9707	1409-G	0.002	2.7 MHz	55.00
1409-9711	1409-K	0.005	1.3 MHz	55.00
1409-9712	1409-L	0.01	750 kHz	55.00
1409-9713	1409-M	0.02	430 kHz	60.00
1409-9718	1409-R	0.05	210 kHz	65.00
1409-9720	1409-T	0.1	120 kHz	70.00
1409-9721	1409-U	0.2	70 kHz	80.00
1409-9724	1409-X	0.5	35 kHz	120.00
1409-9725	1409-Y	1.0	17 kHz	200.00



PRECISION DECADE CAPACITOR

Type 1423-A

- 100 pF to 1.111 μF
- ±0.05 % accuracy
- two- or three-terminal connection




This capacitor is a versatile tool for calibration laboratories and production-line testing. With it a bridge can be standardized to an accuracy exceeded only by that of the highest quality, individually certified laboratory standards such as the GR 1404 Reference Standard Capacitors. Used with a limit bridge, such as the GR 1605-A Impedance Comparator, the 1423 facilitates fast and accurate production-line measurements of arbitrary capacitance values with minimum setup time.


Any value of capacitance from 100 pF to 1.111 μ F, in steps of 100 pF, can be set on the four decades and will be known to an accuracy of 0.05%. The terminal capacitance values are set precisely to the nominal value and

can be readjusted later at calibration intervals, if necessary, without disturbance of the main capacitors.

The 1423 consists of four decades of high-quality silvered-mica capacitors similar to those used in the GR 1409 Standard Capacitors. The capacitors and associated switches are mounted in an insulated metal compartment, which in turn is mounted in a complete metal cabinet. This double-shielded construction ensures that capacitance at the terminals is the same for either the three-terminal or the two-terminal method of connection (except for a constant difference of about one picofarad). This external capacitance can be included in the two-terminal calibration by the adjustment of a single trimmer.



(Left) Change in capacitance as a function of frequency. These changes are referred to the values that the capacitors would have if there were neither interfacial polarization nor series inductance. The 1-kHz value on the plot should be used as a basis of reference in estimating frequency errors. (Right) Dissipation factor as a function of frequency.



specifications

Nominal Values: 100 pF to 1.111 μ F in steps of 100 pF.

Accuracy: ±(0.05% + 0.05pF) at 1 kHz, calibrated in the three-terminal connection. Two-terminal connection (capacitor inserted into Type 777-Q3 Adaptor) adds about 1.3 pF reading.

Stability: $\pm (0.01\% + 0.05pF)$ per year.

Certificate: A certificate is supplied certifying that each component capacitor was adjusted by comparison, to a precision better than $\pm 0.01\%$, with working standards whose absolute values are known to an accuracy typically $\pm 0.01\%$, determined and maintained in terms of reference standards periodically calibrated by the National Bureau of Standards.

Frequency: See curves for typical variation of capacitance and dissipation factor with frequency.

Dissipation Factor: Not greater than 0.001, 0.0005, and 0.0003 for capacitances of 100 to 1000 pF, 1100 to 2000 pF, and 2100 pF to $1.1110~\mu\text{F}$, respectively.

Temperature Coefficient of Capacitance: Approx +20 ppm per degree between 10° and 50° C.

Insulation Resistance: > 5 \times $10^{_{10}}$ Ω to 0.1 μF and > 5 \times $10^{_{9}}$ Ω from 0.1 μF to 1.111 $\mu F.$

Maximum Voltage: 500 V peak, up to 10 kHz.

Accessories Supplied: Two Type 777-Q3 Adaptors.

Mounting: Rack-Bench Cabinet.

Dimensions (width x height x depth): Bench, $19 \times 7\frac{1}{4} \times 10\frac{1}{2}$ in. (485 x 185 x 270 mm); rack, $19 \times 7 \times 8\frac{1}{2}$ in. (485 x 180 x 220 mm). Weight (both models): Net, 26 lb (12.0 kg); shipping, 39 lb (18 kg).

Catalog Number	Description	Price in USA
1423-9801 1423-9811	Precision Decade Capacitor 1423-A, Bench Model 1423-A, Rack Model	\$800.00 800.00





- stable to 0.05% per year
- for rf impedance calibrations

COAXIAL CAPACITANCE STANDARDS

Type 1406

The 1406 Coaxial Capacitance Standards are stable, low-loss air capacitors with small, stable and known series inductance. This permits the accurate, traceable calibration of high-frequency bridges and other impedancemeasuring instruments.

REPEATABLE COAXIAL CONNECTION

GR900® precision coaxial connectors are used on the 1406's; their stability and repeatable performance have been proven in use at frequencies as high as 9 GHz. The use of coaxial connectors also meets the high-frequency calibration requirements of the National Bureau of Standards.

INSTRUMENT CALIBRATION

The 1406 standards can be connected directly to instruments equipped with GR900 precision connectors and to others through appropriate adaptors. The Type 900-Q9 adaptor is offered to facilitate connection to 1/4" x 28 threaded studs or tapped holes on 3/4" to 1" centers. Series inductance and resistance have been kept low in the 900-Q9 and, when other adaptors are used, these quantities should be known to permit correcting for their effects at high frequencies.

These standards can be calibrated at audio frequencies

with the GR 1615 Capacitance Bridge and the 1615-P2 Coaxial Adaptor, which has an adjustment for compensating for its capacitance and that of the binding posts and thus permits direct-reading measurements.

specifications

Calibration: A certificate of calibration is supplied with each unit, giving the measured capacitance at 1 kHz and at a specified temperature and relative humidity. The measured capacitance is the capacitance at the reference plane of the GR900 connector. This value is obtained by comparison, to a precision better than ±0.01%, with working standards whose absolute values are known to an accuracy typically ±0.01%, determined and maintained in terms of reference standards periodically calibrated by the National Bureau of Standards.

Stability: The capacitance change is less than 0.05% per year.

Accuracy: Capacitance adjusted to within 0.1% of nominal value. Residual Impedances: See table. Dissipation factor varies as the 3/2 power of frequency above about 100 kHz. Insulation resistance is greater than 1012 ohms at 23°C and less than 50% RH. Temperature Coefficient of Capacitance: Typically 10 to 20 ppm/°C between 20°C and 70°C.

Accessories Available: Adaptors 1615-P2 for convenience in cali-brating with 1615-A Capacitance Bridge and 900-Q9 for connecting 1406 to ¼-in. x 28 threaded stud (GR 938 Binding Post) or tapped

Terminal: GR900 precision coaxial connector.

Mounting: Aluminum panel and cylindrical case.

Dimensions (diameter x height): $3\frac{1}{6}$ x $5\frac{1}{4}$ in. (78 x 135 mm).

Weight: Net, 11/2 lb (0.7 kg); shipping, 4 lb (1.9 kg).

Catalog		talog Nominal		Typical Dissip	ation Factor	Typical	Price
Number Type	Туре	Capacitance	Peak Volts	1 kHz (40% RH)	1 MHz	Inductance	in USA
1406-9701	1406-A	1000 pF	700	3 x 10─6	50 x 10−6	8.6 nH	\$120.00
1406-9702	1406-B	500 pF	900	5 x 10-6	30 x 10─₺	8.4 nH	115.00
1406-9703	1406-C	200 pF	1200	20 x 10−6	25 x 10−6	8.1 nH	110.00
1406-9704	1406-D	100 pF	1500	30 x 10−6	20 x 10─ ⁶	7.6 nH	105.00
1406-9705	1406-E	50 pF	1500	50 x 10−6	15 x 10─6	6.7 nH	100.00
1615-9602	1615-P2 Co	axial Adaptor, GR9	00 to 1615 Br	ridge			75.00
0900-9874	900-Q9 Ada	ptor, GR900 to bind	ding posts	_			50.00



- 1, 2, and 5 pF
- rf standards
- GR900® connectors

COAXIAL CAPACITANCE STANDARDS

Type 1405

Extending the available values of rf capacitance downward, the 1405 standards permit impedance-measuring instruments to be calibrated at even higher frequencies accurately and with traceability to the National Bureau of Standards.

specifications

Calibration: A certificate of calibration is supplied with each unit, giving the measured capacitance at 1 kHz and at a specified temperature and relative humidity. The measured capacitance is the capacitance at the reference plane of the GR900 connector. This value is obtained by comparison, to a precision better than ±0.001 pF, with working standards whose absolute values are known to an accuracy typically ±0.01%, determined and maintained in terms of reference standards periodically calibrated by the National Bureau of Standards.

Accuracy: Capacitance adjusted to within tolerance given in table.

Residual Impedances: Dissipation factor at $1~\text{kHz}, <30~\times~10^{-6}$ for -C, -D; $<40~\times~10^{-6}$ for -E; insulation resistance is $>10^{12}~\Omega$ at $23^{\circ}\text{C}, <50\%$ RH. Effect of series inductance and other factors is given in table below in terms of the frequency at which it causes a 10% increase in measured capacitance.

Accessories Available: Adaptors 1615-P2 for calibrating with GR 1615 bridge and 900-Q9 for connecting standard to ¼-inch x 28 threaded stud (GR 938 Binding Post) or tapped hole.

Terminal: GR900 precision coaxial connector.

Dimensions (diameter x height): 11/6 x 25/6 in. (27 x 59 mm).

Weight: Net, 4 oz (103 g); shipping, 5 oz (150 g).

Catalog Number	Туре	Nominal Capac- itance	Accuracy	Peak Voits	Frequency for 10% C Increase	Price in USA
1405-9702	1405-C 1405-D	5 pF	±0.010 pF ±0.005 pF	1 kV 1 kV	0.75 GHz 1.4 GHz	\$55.00 55.00
1405-9701 1405-9700	1405-D 1405-E	2 pF 1 pF	±0.005 pF	3 kV	1.4 GHZ	55.00

standard capacitors

STANDARD AIR CAPACITOR

Type 1403


- 1000 pF to 0.001 pF
- calibration accuracy: $\pm 0.02\% \pm 0.01 fF$



The 1403 Standard Air Capacitors are stable, threeterminal standards in decimal values from 0.001 to 1000 pF. Their terminals are arranged to plug directly into the UNKNOWN terminals of the 1615-A Capacitance Bridge.

specifications

Calibration: A certificate of calibration is supplied with each unit giving the measured capacitance at 1 kHz and at a specified temperature. The measured value is the direct capacitance between shielded terminals when the capacitor has at least one



Typical increase (per-cent) in effective direct capacitance, with fre-quency produced by re-sidual inductance.

lead completely shielded and its case connected to a guard point. This value is obtained by comparison, to a precision better than $\pm (0.01\% + 0.00001 \ pF)$, with working standards whose absolute values are known to an accuracy typically $\pm 0.01\%$, determined and maintained in terms of reference standards periodically calibrated by the National Bureau of Standards.

Stability: Capacitance change is less than 0.05% per year.

Residual Impedances: See curves for high-frequency use.

Dissipation Factor: <20 \times 10 $^{-6}$ max at 1 kHz and 50% or less relative humidity.

Peak Voltage: 1500 V, except for 1403-A, which is 700 V.

Temperature Coefficient of Direct Capacitance: Typically 20 to 40 ppm per degree between 20° and 70°C. The larger coefficients apply to the smaller capacitance values.

Terminals: GR874 coaxial connectors, which provide complete shielding of the leads.

Dimensions: Diameter 31/4 in. (78 mm), height 51/4 in. (135 mm),

Weight: Net, 1 lb (0.5 kg); shipping, 4 lb (1.9 kg).

Catalog	Туре	Nominal	Adjustment	Price
Number		Capacitance - pF	Accuracy - %	in USA
1403-9701 1403-9704 1403-9707 1403-9711 1403-9714 1403-9718 1403-9722	1403-A 1403-D 1403-G 1403-K 1403-N 1403-R 1403-V	1000 100 10 1.0 0.1 0.01 0.001	0.1 0.1 0.1 0.1 0.3 1.0	\$95.00 80.00 65.00 65.00 70.00 70.00 70.00

FOUR-TERMINAL CAPACITANCE STANDARD

- 1 μF to 1 farad in decade steps
- accuracy ¼%, 1% at 1 F

Type 1426



The 1426 capacitance standard is of great value in calibrating four-terminal, high-capacitance bridges like the GR 1617. With calibration, the 1426 can be used as a two-terminal standard at 120 Hz and at settings up to

The 1426 consists of a 1-µF polystyrene capacitor and a transformer that multiplies the effective capacitance to higher values. This arrangement gives stability unattainable with very-high-value true capacitors. Such construction prohibits general circuit applications and particularly uses with dc applied to the capacitor.

specifications

Capacitance: 1 µF to 1 F in 7 switch-selected decade values.

Accuracy: $\pm 1/4\%$, except $\pm 1/2\%$ for 100 mF and $\pm 1\%$ for 1 F; measured at 120 Hz at 23°C at <Max Volts specified below. Measurements must use 4-terminal connections with all but the 1_{FF} value; at 1 F, lead arrangement must be as prescribed in operating instruction manual.

Dissipation Factor: <0.0003 for 1 μF at 120 Hz; <0.1 for larger

Max Ac Voltage: Voltage 10:1 larger than specified will not damage standards above 1 $\mu \rm F$ but will cause an error of approx 1%.

 $1 \mu F$ 10 μF 100 μF 1 mF 10 mF 100 mF Capacitance Max Ac Volts 100 V 2 V 1 V 0.3 V 0.2 V 0.2 V 0.05 V

Max Dc Voltage: No dc permissible as values above 1 μ F are dc short circuits and could be changed in value by dc current; 100 V max for 1- μ F standard only.

Temperature Coefficient: 140 ppm/°C typical.

Frequency Characteristic: $1\text{-}\mu\text{F}$ standard is true capacitor with 170-kHz resonance; other values very frequency dependent. Add 14% error at 100 Hz, add 1% from 60 to 150 Hz.

Dimensions (width x height x depth): $8 \times 5\% \times 8$ in. (205 x 150

Weight: Net, 71/2 lb (3.5 kg); shipping, 11 lb (5 kg).

Catalog Number	Description	Price in USA	
1426-9700	1426 Four-Terminal Capacitance Standard	\$275.00	



DECADE CAPACITORS



Type 1424-A. Type 1424-M is similar in appearance.



Type 1425-A

- 10-μF Standard Decade Polystyrene Dielectric Type 1424-A
- 100-μF Standard Decade Polystyrene Dielectric Type 1425-A
- 10-µF Decade Paper Dielectric Type 1424-M

TYPE 1424-A

Polystyrene capacitors, combined in $10~1\text{-}\mu\text{F}$ units, are housed in two hermetically sealed, non-ferrous metal cases with Teflon*-insulated high terminals, the cases being the common (LOW) terminal. The aluminum outer cabinet and panel are insulated from both capacitor terminals, so that either two- or three-terminal connections can be used.

Residual series inductance and resistance have been minimized by the use of current-sheet conductors, ribbon leads, and multiple switch contacts.

TYPE 1424-M

This capacitor is a 1-microfarad-per-step decade, which

* Registered trademark of E. I. duPont de Nemours and Company.

has less rigorous performance specifications than the 1424-A and a correspondingly lower price. Sealed foil-paper capacitors of noninductive extended-foil construction are used with a viscous impregnant to improve stability.

TYPE 1425-A

Polystyrene capacitors are connected in 10- μ F steps. The configuration and dimensions of binding posts, bus, studs, and current-sheet connectors are arranged to minimize residuals. Switching resistance is kept low through the use of tapered plug connectors, rather than rotary switches. Binding posts have large contact areas and are easily tightened by hand to minimize contact resistance.

— See GR Experimenter for July 1965.

specifications


Accuracy: The accuracy stated in the table below is guaranteed for two years under the terms of our standard warranty, if the capacitor has not been damaged by excessive current or voltage. Certificate: 1424-A and 1425-A: A certificate is supplied giving measured values obtained by comparison, to a precision better than $\pm 0.01\%$, with working standards whose absolute values are known to an accuracy better than $\pm 0.05\%$, determined and main-

tained in terms of reference standards periodically measured by the National Bureau of Standards. 1424-M: A certificate is supplied, certifying the accuracy of adjustment in terms of reference standards, periodically measured by the National Bureau of Standards.

Frequency Characteristic: Calibration and adjustment are made at 1 kHz. Plots of typical change in capacitance and dissipation factor with frequency are given in the calibration certificate.

Туре	1424-A	1425-A	1424-M
Total Capacitance	10 μF	100 μF	10 μF
Capacitance per Step	1 μF	10 μF	1 μF
Dielectric	Polystyrene	Polystyrene	Paper
Adjustment Accuracy at 1 kHz	±0.25%	±0.25%	±1%
Stability	±0.05%/year	±0.05%/year	±0.35%/year
Dissipation Factor at 1 kHz	< 0.0003	< 0.0004	<0.005
Insulation Resistance	>10 ^a ΩF	>10° ΩF	>10⁴ ΩF
Voltage Recovery *	<0.1%	<0.1%	<5%
Temp Coefficient of Capacitance (typical) ppm/°C	-140	-140	+180
Max Operating Temperature °C	65	65	90
Max Safe Voltage	500 V, peak, below 10 kHz	25 V, peak, below 10 kHz	500 V, peak, up to 2 kHz
Dimensions Width, height, depth; inches (mm)	91/2, 73/4, 8 (245, 195, 205)	9¾, 19¼, 8¼ (240, 485, 205)	91/2, 6, 8 (245, 150, 205)
Net Weight Ib (kg)	161/2 (7.5)	461/2 (21.5)	7¾ (3.6)
Shipping Weight Ib (kg)	19 (9)	67 (31)	11 (5)
Catalog Number	1424-9701	1425-9701	1424-9713
Price in USA	\$410.00	\$1950.00	\$210.00

^{*} Dielectric absorption



DECADE CAPACITORS

Type 1419



- 100 pF to 1.1 μF
- choice of models
- two- or three terminal connection

Type 1419 Decade Capacitors are offered in four models using three different dielectric materials to satisfy a variety of needs.

Types 1419-A and -B (Polystyrene)

Capacitance and dissipation factor constant with frequency, essentially noninductive, very low dielectric absorption. The dielectric is specially prepared of purified high-molecular-weight polystyrene, having very high resistance and freedom from interfacial polarization. Moisture sealing with Teflon* feed-through insulators assures high performance under adverse humidity conditions.

Type 1419-K (Silvered Mica)

Higher accuracy, low dissipation factor, and $+35 \pm 10$ ppm/°C temperature coefficient (10-50°C) for use in higher ambient temperatures.

Type 1419-M (Molded Silvered Mica and Paper)

For economy and excellent performance characteristics, sealed foil-and-paper capacitors are used in the highestvalue decade and EIA Characteristic-C molded silvered micas in the smaller two.

specifications

TYPE NUMBER	1419-A	1419-B	1419-K	1419-M	
Dielectric	Polystyrene	Polystyrene	Silvered Mica	Paper and Silvered Mica (Molded)	
Maximum Capacitance of Box (μF)	1.110	1.1110	1.110	1.110	
In Steps of (μF)	0.001	0.0001	0.001	0.001	
Dials	3	4	3	3	
Zero Capacitance, typical 2-terminal connection	37 pF	50 pF	41 pF	35 pF	
3-terminal connection	15 pF	20 pF	13 pF	16 pF	
Accuracy ¹ 2-terminal connection ²	±1%	±(1% + 2 pF)	±0.5%	±1.5% on highest decade ±1% on others	
3-terminal connection	±1% except ±1.5% on smallest decade	+1% or -(2% + 4 pF)	±0.5% except ±1% on smallest decade	±1.5% on highest decade ±1% on others	
Dissipation Factor at 1 kHz	<0.0002		< 0.0003	< 0.005	
Insulation Resistance at 100 V, 25°C, 50% RH, (ohms), typical	>1012		>5 × 10°	>10°	
Max Voltage ³ (dc or peak)	500 V up t	o 35 kHz	500 V up to 10 kHz	500 V up to 1 kHz	
Max Operating Temperature (C)	65		75	90	
Voltage Recovery⁴	<0.:	1%	<3%	<5% on highest decade	
Resonant Frequencies (typical)	1 μF-400 kHz; 0.1 μF-1	MHz; 0.01 μF—2.7 MHz;	0.001 μF7.8 MHz; 0.0001 μF23 MHz		
Dc Cap/ 1-kHz Cap	<1.0	001	Typically 1.03		
Cabinet			Lab-bench		
Over-all Dimensions — in. (mm)	13 x 45% x 5 (330 x 110 x 130)	1 6 % x 4% x 5 (415 x 110 x 130)	141/8 x 51/2 x 6 (359 x 140 x 153)	141/8 x 51/2 x 6 (359 x 140 x 153)	
Net Weight — Ib (kg)	8% (3.8)	101/2 (4.8)	11¼ (5.5)	6¼ (2.9)	
Shipping Weight — Ib (kg)	10 (4.6)	11 (5)	18 (8.5)	8 (3.7)	
Catalog Number	1419-9701	1419-9702	1419-9711	1419-9713	
Price in USA	\$210.00	\$270.00	\$435.00	\$200.00	

Capacitance increments from zero position are within this percentage of the indicated value for any setting at 1 kHz.


^{*} Registered trademark of E. I. duPont de Nemours and Company.

² Units are checked with switch mechanism high, electrically, and the common lead and case grounded.

³ At frequencies above the indicated max, the allowable voltage decreases and is (approx) inversely proportional to frequency. These limits correspond to a temperature of 40°C at max setting of each decade in box.


Final % of original charging voltage after a charging period of one hour and a 10-second discharge through a resistance equal to one ohm per volt of charging.





1419 Decades

(Left) Typical plot of change in capacitance at maximum setting of each decade as a function of frequency. The capacitance curves are referred to the value the capacitor would have if there were no interfacial polarization and no series inductance. Since the capacitors are adjusted to their rated accuracy at 1 kHz, the 1-kHz value on the plots should be used as a basis of reference in estimating the frequency error. (Right) Typical plot of dissipation factor as a function of frequency.



- 50 pF to 1.11115 μF
- better than 1-pF resolution
- \blacksquare accuracy $\pm (1\% + 5 pF)$
- low loss, leakage, dielectric absorption

DECADE CAPACITOR

Type 1412-BC




The wide capacitance range and high resolution of this decade capacitance box make it exceptionally useful in both laboratory and test shop. Owing to its fine adjustment of capacitance, it is a convenient variable capacitor to use with the 1605-A Impedance Comparator. The polystyrene dielectric used in the decade steps is necessary for applications requiring low dielectric absorption and constancy of both capacitance and dissipation factor with frequency.

Four decades of polystyrene capacitors and a variable air capacitor are used, mounted in a double-shield box. The double shielding provides 2-terminal and 3-terminal capacitances that are the same except for the capacitance between the terminals. The variable air capacitor with a linear ΔC of 100 pF and a resolution of better than 1 pF

provides continuous adjustment between the 100-pF steps of the smallest decade.

- See GR Experimenter for August 1966.

The double shielding used in the 1412-BC Decade Capacitor keeps CHG very small. This capacitance is the difference between the 3-terminal and 2-terminal capacitance of the box; CLG is approx 125 pf.



specifications

Capacitance: 50 pF to 1.11115 μF in steps of 100 pF with a 0- to 100-pF variable air capacitor providing continuous adjustment with divisions of 1 pF. Capacitances for 2- and 3-terminal connections differ by about 1 pF.

Min Capacitance: 50 pF with all controls set at zero.

Dielectric: Polystyrene for decade steps.

Accuracy: $\pm (1.0\% + 5 \text{ pF})$ at 1 kHz, for total capacitance including 50-pF minimum.

Temperature Coefficient: -140 ppm/°C (nominal).

Frequency Characteristics: Dc Cap/1-kHz Cap <1.001. At higher frequencies the increase is approx $\Delta C/C=(f/f_r)^2$. The resonant frequency, f_r , varies from over 400 kHz for a capacitance of 1 μF to about 27 MHz for a capacitance of 150 pF when connections are made to the front terminals. f_r is about 300 kHz and 70 MHz for rear connections and the same capacitances.

Max Operating Temperature: 65°C.

Dielectric Absorption (Voltage Recovery): 0.1% max.

Dissipation Factor: 150 to 1000 pF, 0.001, max, at 1 kHz; over 1000 pF, 0.0002, max, at 1 kHz.

Insulation Resistance: 1012 ohms, min.

Max Voltage: 500 V peak up to 35 kHz.

Terminals: Four 938 Binding Posts with grounding link are provided on the panel. Two of the binding posts are connected to the case and located for convenient use with patch cords in 3-terminal applications. Access is also provided to rear terminals for relay-rack applications.

Mounting: Lab-Bench Cabinet. Brackets are provided for rack mounting.

Dimensions (width x height x depth): $17\frac{1}{4}$ x $3\frac{1}{2}$ x 6 in. (440 x 89 x 155 mm).

Weight: Net, $8\frac{1}{2}$ lb (3.9 kg); shipping, 10 lb (4.6 kg).

Catalog Number	Description	Price in USA
1412-9410	1412-BC Decade Capacitor	\$250.00

€

STANDARD INDUCTOR

- stable within ±0.01% per year
- low, known temperature coefficient
- minimized connection errors
- toroidal free from external fields

Type 1482



SOURH E O. 15.
NITAS TO GALESCATION SCRIPTIONS

TRACELED HOLOGINA

TRA

1482-D

1482-A

The 1482 is an accurate, highly stable standard of self inductance for use as a low-frequency reference or working standard in the laboratory. Records extending over 11 years, including those of inductors that traveled to national laboratories in several countries for calibration, show long-term stabilities well within $\pm 0.01\%$.

Each inductor is a uniformly wound toroid on a ceramic core. It has a negligible external magnetic field and hence essentially no pickup from external fields. The inductor is resiliently supported in a mixture of ground cork and

silica gel, after which the whole assembly is cast with a potting compound into a cubical aluminum case.

Sizes of 500 μ H and above have three terminals, two for the inductor leads and the third connected to the case, to provide either a two- or three-terminal standard. The 50-, 100-, and 200- μ H sizes have three additional terminals for the switching used to minimize connection errors, as described in the introduction to the inductance section.

For comparing other inductors with these standards, the 1632-A Inductance Bridge is recommended.

specifications

Inductance Range: See table.

Accuracy of Adjustment: See table.

Calibration: A certificate of calibration is provided with each unit, giving measured values of inductance at 100, 200, 400, and 1000 Hz, with temperature and method of measurement specified. These values are obtained by comparison, to a precision, typically, of better than $\pm 0.005\%$, with working standards whose absolute values, determined and maintained in terms of reference standards periodically certified by the National Bureau of Standards, are known to an accuracy typically $\pm (0.02\% + 0.1~\mu\text{H})$ at 100 Hz.

Stability: Inductance change is less than $\pm 0.01\%$ per year.

Dc Resistance: See table for representative values. A measured value of resistance at a specified temperature is given on the certificate of calibration.

Low-Frequency Storage Factor Q: See table for representative values of Q at 100 Hz (essentially from dc resistance). An indi-

vidual value of Q, calculated from the measured dc resistance, is given on each certificate of calibration.

Temperature Coefficient of Inductance: Approx 30 ppm per °C. Minute temperature corrections may be computed from dc resistance changes. A 1% increase in resistance, produced by a temperature increase of 2.54°C. corresponds to 0.0076% increase in inductance.

Resonant Frequency: See table for representative values. A measured value is given on the certificate of calibration.

Max Input Power: For a rise of 20°C, 3 W; for precise work, a rise of 1.5° C, 200 mW. See table for corresponding current limits.

Terminals: Jack-top binding posts on ¾-in. spacing with removable ground strap.

Mounting: Aluminum cabinet with handle and rubber feet.

Dimensions (width x height x depth): $6\frac{1}{2}$ x $6\frac{1}{2}$ x 8 in. (165 x 165 x 205 mm).

Weight: Net, 111/2 lb (5.5 kg); shipping, 13 lb (6 kg).

Catalog Number	Description	Nominal Induct- ance	Adjustment Accuracy	*Resonant Frequency	*Dc Resistance	*Q at	Milliam rms i	or,	Price
Hamber	Description	ance	(Percent)	(kHz)	(Ohms)	100 Hz	200 mW	3 W	in USA
	Standard Inductor								
1482-9701	1482-A	50 μH	±0.5	3100	0.039	0.81	2260	8770	\$195.00
1482-9702	1482-B	100 μΗ	±0.25	2250	0.083	0.76	1550	6010	195.00
1482-9703	1482-C	200 μΗ	±0.25	1400	0.15	0.84	1150	4470	195.00
1482-9704	1482-D	500 μH	±0.1	960	0.38	0.83	725	2810	195.00
1482-9705	1482-E	1 mH	±0.1	800	0.84	0.75	490	1890	175.00
1482-9706	1482-F	2 mH	±0.1	580	1.52	0.83	360	1400	155.00
1482-9707	1482-G	5 mH	±0.1	320	3.8	0.83	230	890	150.00
1482-9708	1482-H	10 mH	±0.1	220	8.2	0.77	156	600	145.00
1482-9710	1482-J	20 mH	±0.1	145	14.5	0.87	117	450	145.00
1482-9711	1482-K	50 mH	±0.1	84	36.8	0.85	74	280	145.00
1482-9712	1482-L	100 mH	±0.1	71	81	0.78	50	192	150.00
1482-9713	1482-M	200 mH	±0.1	39.0	109	1.15	43	166	155.00
1482-9714	1482-N	500 mM	±0.1	24.5	280	1.12	27	103	160.00
1482-9716	1482-P	1 H	±0.1	14.6	616	1.02	18	70	190.00
1482-9717	1482-Q	2 H	±0.1	10.6	1125	1.12	13.3	52	220.00
1482-9718	1482-R	5 H	±0.1	6.8	2920	1.08	8.3	32	290.00
1482-9720	1482-T	10 H	±0.1	4.9	6400	0.98	5.6	22	385.00

^{*} Representative values. Actual values given on certificate.



VARIABLE INDUCTOR

Type 107

- 20:1 continuous variation with series or parallel connections
- mutual- and self-inductance calibration



The 107 finds its greatest uses in the laboratory as an adjustable standard of moderate accuracy for measurements of self and mutual inductance, and as a circuit element in bridges, oscillators, and similar equipment.

Rotor and stator coils are mounted concentrically. The effective inductance depends upon the position of the rotor with respect to the stator.

In most models stranded wire is used, in which the separate strands are insulated from one another. The coils are impregnated and baked in a synthetic varnish before being securely mounted on the phenolic panel.

Dial is direct reading in inductance for the series connection of the coils. Inductance for the parallel connection is one-fourth the value shown by the dial.

specifications

Inductance Range: See table below. Dial is direct reading in inductance for the series connection.

Accuracy: Series connection, $\pm 1\%$ of full scale at 1 kHz. Inductance for parallel connection is one-fourth the series value within $\pm (1\% \ + \ 0.01 \ \mu \text{H})$ of the former. Mutual-inductance accuracy is $\pm 2.5\%$ of full-scale (mutual) value. The formula for mutual inductance is engraved on the nameplate. Under our standard warranty, this accuracy is guaranteed for 2 years.

Frequency Characteristics: The fractional increase in inductance with frequency will be f2/fr2 where f is the operating frequency and fr the natural frequency, which can be calculated from


$$f_{\textrm{r}} = \frac{1}{2\pi\sqrt{LC_{\textrm{o}}}}.$$
 Values of $C_{\textrm{o}}$ are tabulated below. See plot for

change in Q with frequency.

Max Power and Current: Current for 15 W max dissipation, corresponding to a temperature rise of $40\,^{\circ}\text{C}$, is given in the table below and is engraved on the nameplate.

Dc Resistance: See table below. These series-connection values are engraved on the nameplate. For parallel connections the resistance is approx 1/4 the tabulated values.

Terminals: Standard 34-in. spacing, jack-top binding posts pro-



Storage factor, Q, versus frequency at full-scale series connection.


vide separate connections to rotor and stator. Series and parallel connections are made by means of links.

Mounting: All units are mounted on phenolic panels and enclosed in unshielded hardwood cabinets.

Dimensions: $6\frac{1}{2}$ x $6\frac{1}{2}$ x $8\frac{3}{4}$ in. (165 x 165 x 220 mm).


Weight: Net, 5 lb (2.3 kg); shipping, 10 lb (4.6 kg).

0.1.1	<i>i</i> ii	Self-Inductance		Mutual	Typical C. Values		Dc Resistance	Maximum Current	Price
Catalog Number	Description	Series	Parallel	Inductance	Series	Parallel	ohms	amperes	in USA
	Variable Inductor								
0107-9710	107-J	9-50 μH	2.25-12.5 μΗ	0-10.8 μΗ	35 pF	57 pF	0.05	16	\$150.0
0107-9711	107-K	90-500 μΗ	22.5-125 μΗ	0-110 μΗ	40 pF	72 pF	0.38	6	150.0
0107-9712	107-L	0.9-5 mH	0.225-1.25 mH	0-1.1 mH	39 pF	73 pF	5.0	1.7	150.0
0107-9713	107-M	9-50 mH	2.25-12.5 mH	0-11 mH	34 pF	41 pF	36	0.65	150.0
0107-9714	107-N	90-500 mH	22.5-125 mH	0-110 mH	34 pF	41 pF	450	0.17	150.0



DECADE-INDUCTOR UNIT

Type 940



Each 940 Decade-Inductor Unit is an assembly of four inductors (relative values, 1, 2, 2, 5) wound on molybdenum-permalloy dust cores, which are combined by switching to give the eleven successive values from 0 to 10. The decade switch has high-quality ceramic statorand-rotor members and well-defined ball-and-socket detents. All contacts are made of a silver alloy and have a positive wiping action.

specifications

Accuracy: Each unit is adjusted so that its inductance at zero frequency and initial permeability will be the nominal value within the accuracy tolerance given in the following table:

Unit	940-DD	940-E	940-F	940-G	940-H
Inductance per step	100 μΗ	1 mH	10 mH	100 mH	1 H
Accuracy	±2%	±2%	±1%	±0.6%	±0.6%

Under our standard warranty, this accuracy is guaranteed for 2 years if the inductor has not been damaged.

Frequency Characteristics: For any specific operating frequency, Figure 2 shows the percentage increase in effective series inductance (above the value when f=0), which is encountered with the extreme settings of each of the five decade-inductor units when the chassis is floating. Interpolation may be used for intermediate settings.

Change in Inductance with Current: Fractional change in initial inductance with ac current for each type of toroid is shown in the normal curves, Figure 1, in terms of the ratio of the operating current, I, to I₁, the current for 0.25% change, solid line (0.1%, broken line). For ratios below unity, inductance change is directly

proportional to current. Values of I₁, listed below, are approximate and are based on the largest inductor in the circuit for each setting.

Incremental Inductance: Dc bias current \mathbf{I}_b will reduce the initial inductance as shown in the incremental curves, Figure 1.

RMS I: (mA)

				()	
Switch Setting	0.1% Increase	0.25% Increase			
	940-DD	940-E	940-F	940-G	940-H
1	141	17	5.4	1.7	0.54
2, 3, 4	100	12	3.8	1.2	0.38
5, 6, 7, 8, 9, 10	63	8	2.4	0.8	0.24

Storage Factor Q: See Figure 3:

Dc Resistance: Approx 45 Ω per henry.

Temperature Coefficient: Approx $-25~{\rm ppm}$ per degree C between $16\,^{\circ}$ and $32\,^{\circ}{\rm C}$.

Max Safe Current: Approx 200 times the pertinent I₁ value (30 times for the 940-DD). Max current engraved on dial.

Terminals: Solder lugs. Circuit insulated from chassis.

Mounting: Hardware included, with dial plate and knob. Dimensions (width x height x depth): $8 \times 3\frac{1}{2} \times 4\frac{1}{4}$ in. (205 x 90 x 110 mm).

Weight: Net, 31/2 lb (1.6 kg); shipping, 6 lb (2.8 kg).

Catalog Number	Description	Indu Total	ctance Steps	Price in USA
	Decade Inductor			
0940-9810	940-DD	1 mH	100 μΗ	\$180.00
0940-9705	940-E	0.01 H	0.001 H	170.00
0940-9706	940-F	0.1 H	0.01 H	120.00
0940-9707	940-G	1 H	0.1 H	180.00
0940-9708	940-H	10 H	1 H	195.00




Figure 1. Percentage change in normal and incremental inductance with ac and bias current. Incremental curve is limited to an ac excitation less than I₁.




Figure 2. Change in effective inductance with frequency for the 940 Decade-Inductor Units.




Figure 3. Variation of Q for the maximum inductance of each 940 Decade-Inductor Unit at low excitation levels. Dashed curves correspond to use with chassis floating.



DECADE INDUCTOR

Type 1491



- shielded toroidal cores for small mutual inductance little effect from external fields
- sealed against moisture



The 1491 Decade Inductor is an assembly of several 940 Decade-Inductor Units in a single metal cabinet. The units have no electrical connection to the panel, but a separate ground terminal is provided, which can be connected to the adjacent low terminal, leading to the smallest decade.

These inductance decades are convenient elements for use in wave filters, equalizers, and tuned circuits throughout the range of audio and low radio frequencies. As components in oscillators, analyzers, and similar equipment, they are especially useful during the preliminary design period, when the ability to vary circuit elements over relatively wide ranges is necessary to determine optimum operating values. As moderately precise standards of inductance they have values of low-frequency storage factor, Q, that are much larger than those of air-core coils.

specifications (see also specifications for 940 decade units)


Frequency Characteristics: Percentage increase in effective series inductance (above the zero-frequency value, $L_{\rm o}$) may be obtained by interpolation in accompanying graph for any setting of the highest-value decade used, when LOW terminal is grounded to cabinet.

Zero Inductance: Approx 1 µH.

Max Voltage: 500 V rms. Switch will break circuit at 500 V if turned rapidly, but voltages above 150 V may cause destructive arcing with switch between detent positions.

Terminals: Binding posts on 34-in. centers; separate ground terminal provided.

Mounting: Lab-Bench Cabinet.



Variation of inductance with frequency, for the 1491 Decade Inductors.


Dimensions (width x height x depth):

1491-A, -B, -C Bench Rack	1234 x 834 x 63/2 in. 19 x 83/4 x 47/8 in.	325 × 225 × 170 mm 485 × 225 × 125 mm
1491-D, -F, -G		
Bench	17 x 8¾ x 6½ in.	435 x 225 x 170 mm
Rack	19 x 8¾ x 47/e in.	485 x 225 x 125 mm

Weight (bench models; add 13/4 lb (0.8 kg) for rack models):

	Net	Shipping (est)
1491-A, -B, -C	18 lb (8.5 kg)	25 lb (11.7 kg)
1491-D, -F	23 lb (10.5 kg)	30 lb (13.7 kg)
1491-G	261/2 lb (12.5 kg)	34 lb (15.5 kg)


Catalog Number		Induc	tance	940's	Price in USA		
Bench	Rack	Description	Total	Steps	Included	Bench	Rack
		Decade Inductor					
1491-9701	1491-9711	1491-A	0.111 H	0.0001 H	DD, E, F	\$515,00	\$540.00
1491-9706	1491-9716	1491-F	1.111 H	0.0001 H	DD, E, F, G	715.00	735.00
1491-9703	1491-9713	1491-C	1.11 H	0.001 H	E, F, G	540.00	565.00
1491-9707	1491-9717	1491-G	11.111 H	0.0001 H	DD, E, F, G, H	895.00	915.00
1491-9704	1491-9714	1491-D	11.11 H	0.001 H	E, F, G, H	725.00	745.00
1491-9702	1491-9712	1491-B	11.1 H	0.01 H	F, G, H	600.00	625.00



STANDARD RESISTOR

Type 1440

- accuracy ±0.01%
- stability ±10 ppm per year
- low thermal emf to copper



These extremely stable resistors are intended for use as laboratory or production standards for calibrating resistance bridges and for substitution measurements.

They are card-type, wire-wound resistors, carefully wound and adjusted. Low-temperature-coefficient Evanohm* wire is used for values above 10 ohms, manganin for the lower-resistance units. All units are heat cycled to reduce strains and are repeatedly checked to elimi-

nate any that show abnormal behavior. They are encased in sealed, oil-filled, diallylphthalate boxes to promote long-term stability and to provide mechanical protection.

The 1440 resistors have low-thermal-emf binding posts and removable banana plugs to provide the four terminals necessary for accurate measurements at low values of resistance. A label on the reverse side lists initial calibration and date, space for future calibration data, and serial number.

— See GR Experimenter for October 1965.

specifications

Accuracy: $\pm 0.01\%$ for all units except those of 1 Ω , which are $\pm 0.02\%$. This accuracy is guaranteed for our standard warranty period of two years, unless the resistor has been damaged by excessive current. Measurements on the low-value units should be made with a four-terminal connection. All measurements at 23°C.

Calibration Accuracy: Resistors are calibrated by comparison, to a precision of ± 20 ppm, with working standards whose absolute values are known typically to ± 10 ppm as determined and measured in terms of reference standards periodically measured by the National Bureau of Standards. The measured deviation from nominal value, at 23°C and 0.01 watt, is entered on the label on the reverse side of the resistor.

Stability: Typically ± 10 ppm per year.

Temperature Coefficient (Max): ± 10 ppm/°C for resistances above 10 Ω ; ± 20 ppm/°C for 10 Ω and below.

Power Rating: 1 W. The corresponding current is indicated on the resistor and in the table below. This dissipation will cause a temperature rise of approx 25°C and a resulting temporary resistance change due to the temperature coefficient. If this rating is exceeded, permanent changes may result.

Residual Impedances: Approx shunt capacitance (2-terminal measurement), 2.5 pF; less for 3-terminal measurement. Typical series inductance, see table.

Approx Frequency Characteristic: See table.

Terminals: Gold-plated jack-top copper binding posts (¾-in. spacing) with banana plugs that are removable and can be replaced by 6-32 screws for installation of soldering lugs.

Dimensions (less terminals): $2\frac{1}{4}$ x $2\frac{1}{32}$ x $\frac{1}{32}$ in. (58 x 64 x 10 mm),

Net Weight (approx): 2 oz (60 g).

Catalog Number	Resistance	Max Current	Typical Inductance	Approx Fre 0.1% Resist Series R	quency for ance Change Paralle! R	Price in USA
Italiiboi	Nesistance	Ourrone	maactanoo	ocrics it	Taranorik	111 00/1
1440-9601	1 Ω	1.0 A	0.12 μΗ	300 kHz	30 kHz	\$30.00
1440-9611	10 Ω	310 mA	0.13 μH	1 MHz	300 kHz	30.00
1440-9621	100 Ω	100 mA	0.20 μΗ	3 MHz	1 MHz	30.00
1440-9631	1 kΩ	30 mA	2.5 μH	2 MHz	1 MHz	30.00
1440-9641	10 kΩ	10 mA		200 kHz	1 MHz	30.00
1440-9651	100 kΩ	3 mA		20 kHz	100 kHz	33.00
1440-9661	1 ΜΩ	1 mA	,	2 kHz	10 kHz	37.00

^{*} Registered trademark of the Wilbur B. Driver Company.

- ±0.05% accuracy
- 5-, 6-, or 7-dial settability
- excellent stability, low cost

DECADE RESISTOR

Type 1434



These laboratory-quality, budget-priced decade boxes are designed for maximum usefulness and economy in laboratory measurement, testing, and development work. Their accuracy is adequate for all but the most exacting applications and their small size and clear readout should be particularly useful in experimental setups using small, modern components.

The 1434-M, -N, and -P contain five step decades of resistance in a small cabinet. The 1434-B and -X, 6-dial boxes, permit small as well as large values of resistance to be set with 3- or 4-place resolution and accuracy. The 1434-QC, a "best buy," has four step decades plus a rheostat to provide 1-ohm resolution in a 1-megohm box.

The larger, seven-decade, 1434-G box is easily converted into a 31/2-inch relay-rack unit by the addition of angle brackets and dress strips, which are furnished. This box has lug terminals available at the rear, as well as at panel binding posts.

DESCRIPTION

High-quality, wire-wound resistors are used in these decades. The low price is made possible by the use of only six resistors per decade instead of ten. These are combined by switching in such a way that there are no discontinuities, that is, the resistance increases stepwise just as if ten resistors were used. The switches have solid-silver-alloy contacts for low resistance and long life.

Resistors are of low-temperature-coefficient Evanohm* wire, except the 1-ohm/step decade, which uses manganin wire, and the 0.1-ohm/step decade, which uses manganin ribbon. The resistors of the 100-ohm/step, 10ohm/step, and 1-ohm/step decades are Ayrton-Perry wound to minimize inductance.

See GR Experimenter for October 1965.

* Registered trademark of the Wilbur B. Driver Company.

specifications

Long-term: Two-year warranty applies to the tolerances given barring damage by excessive current. Tolerances apply at low currents and at dc or low-frequency ac. Over-all: The resistance difference between that at any setting and at the zero setting is equal to the indicated value $\pm (0.05\% + 5 \, \text{m}\Omega)$.

Incremental: See table. This is the accuracy of the change in resistance between any two settings of the same dial.

Zero Resistance: Approx 3 m Ω per dial at low frequencies except for the 1434-QC for which it is approx 30 m Ω .

Max Current: See table; these values also appear on the panel of each decade box. When this max current is passed through a decade, the temporary change in value will be less than the accuracy specification. Currents appreciably higher than this will cause permanent damage.

Total	Resistance	Incremental	Max
Resistance of Decade	Per Step	Accuracy*	Current
1 Ω	0.1 Ω	$\begin{array}{l} \pm 3.0\% \\ \pm 0.3\% \\ \pm 0.08\% \\ \pm 0.05\% \\ \pm 0.05\% \\ \pm 0.05\% \\ \pm 1.005\% \\ \pm 1.005\% \end{array}$	1 A
10 Ω	1.0 Ω		0.3 A
100 Ω	10 Ω		160 MA
1 kΩ	100 Ω		50 MA
10 kΩ	1 kΩ		16 MA
100 kΩ	10 kΩ		5 MA
1 MΩ	100 kΩ		1.6 MA
100-Ω Rheostat**	1 Ω/div		200 MA

* At low currents and low frequencies. ** Used in 1434-QC. Temperature Coefficient: $<\pm 10$ ppm/°C at room temperature, except for the low-valued units where the +0.4%/°C temperature coefficient of the zero resistance must be added.

Frequency Characteristics: Generally similar to those of the 1433 Decades.

Switches: Multiple, solid-silver-alloy switches are used to obtain low and stable zero resistance.

Terminals: Jack-top binding posts on standard ¾-in. spacing. A shield terminal is also provided. The 1434-G has lug connections accessible from the rear.

Mounting: All types except the 1434-G are in small cabinets for bench use. The 1434-G is also designed for bench use but, with the addition of mounting hardware, becomes 3½-in. high, 19-in.

Mechanical Data:

Madala	Wi	dth	He	ight	De	pth	N Wei	et ight	Shi _l We	oping ight
Models	in.	mm	ln.	mm	in.	mm	lb	kg	lb	kg
M, N, P, QC	113/4	300	23/4	70	41/4	110	3	1.4	4	1.9
В, Х	13¾	350	23/4	70	41/4	110	31/4	1.5	4	1.9
G (bench)	17%	442	31/2	89	5	130	6	2.8	7	3.2
G (rack)	19	485	31/2	89	31/2	89	6	2.8	7	3.2


Catalog Number	Description	Total Resistance (Ω)	Resistance Per Step	Number of Decades	Price In USA
	Decade Resistor				
1434-9714	1434-N	11,111	0.1 Ω	5	\$124.00
1434-9713	1434-M	111.110	1.0 Ω	5	119.00
1434-9716	1434-P	1,111,100	10 Ω	5	137.00
1434-9576	1434-QC	1,111,105	1 Ω/div	4 + rheostat	124.00
1434-9702	1434-B	1,111,100	1.0 Ω	6	165.00
1434-9724	1434-X	111,111	0.1 Ω	6	155.00
1434-9707	1434-G	1.111.111	0.1 Ω	7	193.00



DECADE RESISTOR

Type 1433

- ±0.02% accuracy
- good frequency characteristics
- low temperature coefficient
- excellent stability
- low zero resistance



The 1433 Decade Resistors are primarily intended for precision measurement applications where their excellent accuracy, stability, and low zero resistance are important. They are convenient resistance standards for checking the accuracy of resistance-measuring devices and are used as components in dc and audio-frequency impedance bridges. Many of the models can be used up into the radio-frequency range. While they are also useful as substitution boxes for optimizing electronic circuitry, the less expensive Type 1434 Decade Resistors are recommended for such less exacting applications.

The individual decades (510 Decade-Resistance Units) are available for applications requiring only one decade or as components to be built into experimental equipment, production test equipment, or commercial instruments.

specifications


Long-Term Accuracy: Our two-year warranty applies to the tolerances given below unless the resistor is damaged by excessive current. These tolerances apply for low-current measurement at dc or low-frequency ac (see below).

Over-all Accuracy: The resistance difference between that at any

Overall Accuracy: The resistance difference between that at any setting and at the zero setting is equal to the indicated value $\pm(0.02\%+2~\text{m}\Omega).$

Incremental Accuracy: See table. This is the accuracy of the change in resistance between any two settings on the same dial. Max Current: The max current for each decade is given in the table below and also appears on the panel of each decade box and on the dial plate of each decade resistance unit.

Frequency Characteristic: The accompanying plot shows the max percentage change in effective series resistance, as a function of



Max percentage change in series resistance as a function of frequency for Type 510 Decade-Resistance Units.

DESCRIPTION

The 1433 Decade Resistor is an assembly of 510 Decade-Resistance Units in a single cabinet. Mechanical as well as electrical shielding of the units and switch contacts is provided by the attractive aluminum cabinet and panel. The resistance elements have no electrical connection to the cabinet and panel, for which a separate shield terminal is provided.

Each Type 510 Decade-Resistance Unit is enclosed in an aluminum shield, and a knob and etched-metal dial plate are supplied. Each decade has ten resistors in series; the contacts in the lower-valued decades have a silver overlay to ensure stability of resistance, and all the decades have a silver contact on the zero setting to give low and constant zero resistance. Winding methods are chosen to reduce the effects of residual reactances.

frequency for the individual decade units. For low-resistance decades the error is due almost entirely to skin effect and is independent of switch setting, while for the high-resistance units the error is due almost entirely to the shunt capacitance and its losses and is approx proportional to the square of the resistance setting.

The high-resistance decades (510-E, -F, -G, and -H) are very commonly used as parallel resistance elements in resonant circuits, in which the shunt capacitance of the decades becomes part of the tuning capacitance. The parallel resistance changes by only a fraction (between a tenth and a hundredth) of the series-resistance change, depending on frequency and the insulating material in the switch

ing material in the switch.

Characteristics of the 1433's are similar to those of the individual 510's modified by the increased series inductance, Lo, and shunt capacitance, C, due to the wiring and the presence of more than one decade in the assembly. At total resistance settings of approx 1000 ohms or less, the frequency characteristics of any of these decade resistors are substantially the same as those shown for the 510's. At higher settings, shunt capacitance becomes the controlling factor, and the effective value of this capacitance depends upon the settings of the individual decades.


Typical Values of R_{o} , L_{o} , and C for the Decade Resistors:

Zero Resistance (Ro): 0.001 Ω per dial at dc; 0.04 Ω per dial at 1 MHz; proportional to square root of frequency at all frequencies above 100 kHz.

Zero Inductance (Lo): 0.1 μ H per dial + 0.2 μ H.

Effective Shunt Capacitance (C): This value is determined largely by the highest decade in use. With the low terminal connected to the shield, a value of 15 to 10 pF per decade may be





Equivalent circuit of a resistance decade, showing location and nature of residual impedances.

assumed, counting decades down from the highest. Thus, if the third decade from the top is the highest resistance decade in circuit (i.e., not set at zero), the shunting terminal capacitance is 45 to 30 pF. If the highest decade in the assembly is in use, the effective capacitance is 15 to 10 pF, regardless of the settings of the lower-resistance decades.

Temperature Coefficient of Resistance: Less than ± 10 ppm per degree C for values above $100~\Omega$ and ± 20 ppm per degree C for $100~\Omega$ and below, at room temperatures. For the 1433's the box wiring will increase the over-all temperature coefficient of the 0.1- and 0.01- Ω decades.

Switches: Quadruple-leaf brushes bear on lubricated contact studs of %-in, diameter in such a manner as to avoid cutting but yet give a good wiping action. A cam-type detent is provided. There are eleven contact points (0 to 10 inclusive). The switch resist-

ance is less than 0.0005 Ω . The effective capacitance is of the order of 5 pF, with a dissipation factor of 0.06 at 1 kHz for the standard cellulose-filled molded phenolic switch form and 0.01 on the mica-filled phenolic form used in the 510-G and 510-H units. Max Voltage to Case: 2000 V pk.

Terminals: For 1433, low-thermal-emf jack-top binding posts on standard 34-in, spacing; also provisions for rear-panel connections. Shield terminal is provided; 510's have soldering lugs.

Mounting: 1433's in lab-bench cabinet, rack models include mounting hardware; 510's complete with dial plate, knob, template, and mounting screws.

Dimensions and Weights: in. (mm), lb (kg):

	4-dial U, K, J, L, Q	5-dial T, N, M, P, Y	6-dial W, X, B, Z	7-dial F, G, H
Width*	121/4 (315)	14¾ (375)	171/4	(445)
Height		31/2 (89)		5¼ (135)
Depth	5	in. over-all, 4 i	n, behind pan	el
Net Wt*	43/4 (2.2)	5¾ (2.7)	7 (3.2)	8¾ (4.0)
Ship, Wt*	51/2 (2.5)	6½ (3.0)	81/2 (3.9)	101/4 (4.7)

*Data given for bench models. All rack models same except 19 in. wide. Add approx 1 lb for rack-mount hardware. Type 510's $3\%_6$ in. (78 mm) diameter, $3\%_6$ in. (85 mm) behind panel, 11 oz (0.4 kg) net weight.

Catalog Number				Ohms	No. of	T 510 D	Price in USA	
Bench	Rack	Туре	Total Ohms	per Step	No. of Dials	Type 510 Decades Used	Bench	Rack
1433-9700 1433-9702 1433-9704 1433-9706 1433-9708	1433-9701 1433-9703 1433-9705 1433-9707 1433-9709	1433-U 1433-K 1433-J 1433-L 1433-Q	111.1 1111 11,110 111,100 1,111,000	0.01 0.1 1 10 100	4 4 4 4	AA, A, B, C A, B, C, D B, C, D, E C, D, E, F D, E, F, G	\$120.00 122.00 125.00 120.00 154.00	\$128.00 130.00 133.00 128.00 162.00
1433-9710 1433-9712 1433-9714 1433-9716 1433-9718	1433-9711 1433-9713 1433-9715 1433-9717 1433-9719	1433-T 1433-N 1433-M 1433-P 1433-Y	1111.1 11,111 111,110 1,111,100 11,111,000	0.01 0.1 1 10 100	5 5 5 5 5	AA, A, B, C, D A, B, C, D, E B, C, D, E, F C, D, E, F, G D, E, F, G, H	146.50 144.00 147.50 182.50 247.50	154.50 152.00 155.50 190.50 255.50
1433-9720 1433-9722 1433-9724 1433-9726	1433-9721 1433-9723 1433-9725 1433-9728	1433-W 1433-X 1433-B 1433-Z	11,111.1 111,111 1,111,110 11,111,100	0.01 0.1 1 10	6 6 6	AA, A, B, C, D, E A, B, C, D, E, F B, C, D, E, F, G C, D, E, F, G, H	168.50 166.50 210.00 276.00	176.50 174.50 218.00 284.00
1433-9729 1433-9731 1433-9733	1433-9730 1433-9732 1433-9734	1433-F 1433-G 1433-H	111,111.1 1,111,111 11,111,110	0.01 0.1 1	7 7 7	AA, A, B, C, D, E, F A, B, C, D, E, F, G B, C, D, E, F, G, H	191.00 229.00 303.50	199.00 237.00 311.50



DECADE-RESISTANCE

Type 510

	Catalog Number	Туре	Total Resistance Ohms	Resistance Per Step (ΔR) Ohms	Accuracy of Resistance Increments	Max Current 40° C Rise	Power Per Step Watts	ΔL μΗ	C** pF	L。 "H	Price in USA
	0510-9806	510-AA	0.1	0.01	±2%	4 A	0.16	0.01	7.7-4.5	0.023	\$23.00
	0510-9701	510-A	1	0.1	±0.4%	1.6 A	0.25	0.014	7.7-4.5	0.023	17.50
- 1	0510-9702	510-B	10	1	±0.1%	800 mA	0.6	0.056	7.7-4.5	0.023	26.00
-	0510-9703	510-C	100	10	±0.04%	250 mA	0.6	0.11	7.7-4.5	0.023	27.00
- 1	0510-9704	510-D	1000	100	±0.02%	80 mA	0.6	0.29	7.7-4.5	0.023	25.00
- 1	0510-9705	510-E	10,000	1000	±0.02%	23 mA	0.5	13	7.7-4.5	0.023	20.50
- 1	0510-9706	510-F	100,000	10,000	±0.02%	7 mA	0.5	70	7.7-4.5	0.023	21.00
- 1	0510-9707	510-G	1,000,000	100,000	±0.02%	2.3 mA	0.5	_	7.7-4.5	0.023	61.00
н	0510-9708	510-H	10,000,000	1,000,000	±0.02%	0.7* mA	0.5		7.5-4.5	0.023	92.00
М	0510-9604	510-P4	Switch only	(Black Phenoli							11.00
	0510-9511	510-P4L	Switch only	(Low-Loss Phe	nolic Frame)						12.00

^{*}Or a max of 4000 V, pk.

^{**}The larger capacitance occurs at the highest setting of the decade. The values given are for units without the shield cans in place. With the shield cans in place, the shunt capacitance is from 0 to 20 pF greater than indicated here, depending on whether the shield is tied to the switch or to the zero end of the decade.